

Network Working Group
Request for Comments: 4836
Obsoletes: 3636
Category: Standards Track

E. Beili
Actelis Networks
April 2007

Definitions of Managed Objects for
IEEE 802.3 Medium Attachment Units (MAUs)

Status of This Memo

This document specifies an Internet standards track protocol for the Internet community, and requests discussion and suggestions for improvements. Please refer to the current edition of the "Internet Official Protocol Standards" (STD 1) for the standardization state and status of this protocol. Distribution of this memo is unlimited.

Copyright Notice

Copyright (C) The IETF Trust (2007).

Abstract

This document defines a portion of the Management Information Base (MIB) for use with network management protocols in the Internet community. In particular, it defines objects for managing IEEE 802.3 Medium Attachment Units (MAUs). This document obsoletes RFC 3636. It amends that specification by moving MAU type OBJECT-IDENTITY definitions and relevant textual conventions into a separate Internet Assigned Number Authority (IANA) maintained MIB module. In addition, management information is added to enable support for Ethernet in the First Mile (EFM) and 10GBASE-CX4 MAUs.

Table of Contents

1.	Introduction	3
2.	The Internet-Standard Management Framework	3
3.	Overview	4
3.1.	Relationship to RFC 3636	4
3.2.	Relationship to Other MIBs	5
3.2.1.	Relationship to the Interfaces MIB	5
3.2.2.	Relationship to the 802.3 Repeater MIB Module	6
3.3.	Management of Internal MAUs	6
3.4.	Mapping of IEEE 802.3 Managed Objects	6
3.5.	Addition of New MAU Types	9
3.5.1.	dot3MauType OBJECT-IDENTITIES	9
3.5.2.	IANAifMauTypeListBits TEXTUAL-CONVENTION	9
3.5.3.	IANAifMauMediaAvailable TEXTUAL-CONVENTION	9
3.5.4.	IANAifMauAutoNegCapBits TEXTUAL-CONVENTION	10
3.5.5.	JackType TEXTUAL-CONVENTION	10
4.	MAU MIB Definitions	10
5.	IANA-Maintained MAU TC Definitions	46
6.	Security Considerations	62
7.	IANA Considerations	63
8.	Acknowledgments	63
9.	References	64
9.1.	Normative References	64
9.2.	Informative References	66

1. Introduction

This document defines a portion of the Management Information Base (MIB) for use with network management protocols in the Internet community. In particular, it defines objects for managing IEEE 802.3 [IEEE802.3] Medium Attachment Units (MAUs).

The previous version of this document, RFC 3636 [RFC3636], defined a single MIB module. This document splits the original MIB module into two, putting frequently updated object identities and textual conventions into a separate, IANA-maintained MIB module, in order to decrease the need of updating the basic MAU MIB module.

The first version of the IANA-maintained MIB module also extends the list of managed objects to support Ethernet in the First Mile (EFM) and 10GBASE-CX4 interfaces.

Ethernet technology, as defined by the 802.3 Working Group of the IEEE, continues to evolve, with scalable increases in speed, new types of cabling and interfaces, and new features. This evolution may require changes in the managed objects in order to reflect this new functionality. This document, as with other documents issued by this working group, reflects a certain stage in the evolution of Ethernet technology. In the future, this document might be revised, or new documents might be issued by the Ethernet Interfaces and Hub MIB Working Group, in order to reflect the evolution of Ethernet technology.

2. The Internet-Standard Management Framework

For a detailed overview of the documents that describe the current Internet-Standard Management Framework, please refer to section 7 of RFC 3410 [RFC3410].

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. MIB objects are generally accessed through the Simple Network Management Protocol (SNMP). Objects in the MIB are defined using the mechanisms defined in the Structure of Management Information (SMI). This memo specifies a MIB module that is compliant to the SMIV2, which is described in STD 58, RFC 2578 [RFC2578], STD 58, RFC 2579 [RFC2579] and STD 58, RFC 2580 [RFC2580].

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in RFC 2119 [RFC2119].

3. Overview

Instances of these object types represent attributes of an IEEE 802.3 MAU. Several types of MAUs are defined in the IEEE 802.3 CSMA/CD standard [IEEE802.3]. These MAUs may be connected to IEEE 802.3 repeaters or to 802.3 (Ethernet-like) interfaces. For convenience, this document refers to these devices as "repeater MAUs" and "interface MAUs."

The definitions presented here are based on Section 30.5, "Layer Management for 10 Mb/s, 100 Mb/s, 1000 Mb/s, and 10 Gb/s Medium Attachment Units (MAUs)", Section 30.6, "Management for link Auto-Negotiation", and Annex 30A, "GDMO Specifications for 802.3 managed object classes" of IEEE Std. 802.3-2005 [IEEE802.3]. This specification is intended to provide for management of all types of Ethernet/802.3 MAUs.

3.1. Relationship to RFC 3636

The management definitions provided in this document are intended to be a superset of those defined by RFC 3636 [RFC3636].

In order to decrease the need of updating the basic MAU MIB module due to the new MAU type, Media Available state, Auto Negotiation capability and/or Jack type introduction, all relevant object identities and textual conventions have been moved to a separate, IANA-maintained MIB module IANA-MAU-MIB, the first version of which is defined in this document. Thus when a new MAU type, Media Available state, Auto Negotiation capability, and/or Jack type is defined by the IEEE 802.3 working group, only the IANA-maintained module needs to be revised, leaving the basic MAU-MIB module defined in this document unchanged.

In addition, the new definitions are added to the IANA-maintained MIB module, to support Ethernet in the First Mile (EFM) and 10GBASE-CX4 interfaces, defined in IEEE Std 802.3ah-2004 [IEEE802.3ah] and IEEE Std 802.3ak-2004 [IEEE802.3ak] respectively, now part of IEEE Std 802.3-2005 [IEEE802.3].

It should be noted that the changes made in this revision will not be entirely backward-compatible with MIB modules that currently import MAU type object identity descriptors from the MAU-MIB; such modules will need to be revised to import those DESCRIPTORS from the IANA-MAU-MIB. Similarly, any management applications that process the object identity definitions (e.g., to present the DESCRIPTION text to a user) will need to get those definitions from the IANA-MAU-MIB instead of the MAU-MIB. While it is true that changes that require such adjustments are not strictly compliant with the SMIV2 rules

governing MIB module revisions (see [RFC2578] Section 10), in this case continued high maintenance costs that would result from not making these changes make the deviation from the rules justified. It should be noted that the working group was not able to find any examples of MIB modules or management applications that would actually be negatively affected by the changes.

3.2. Relationship to Other MIBs

It is assumed that an agent implementing MAU-MIB will also implement (at least) the 'system' group defined in the SNMPv2 MIB [RFC3418]. The following sections identify other MIBs that such an agent should implement.

3.2.1. Relationship to the Interfaces MIB

The sections of this document that define interface MAU-related objects specify an extension to the Interfaces MIB [RFC2863]. An agent implementing these interface-MAU related objects MUST also implement the relevant groups of the ifCompliance3 MODULE-COMPLIANCE statement of the Interface MIB. The value of the object ifMauIfIndex is the same as the value of 'ifIndex' used to instantiate the interface to which the given MAU is connected.

It is REQUIRED that an agent implementing the interface-MAU related objects in the MAU-MIB will also fully comply with the dot3Compliance2 MODULE-COMPLIANCE statement of the Ethernet-like Interfaces MIB, [RFC3635]. Furthermore, when the interface-MAU related objects are used to manage a 10GBASE-W PHY -- i.e., when ifMauType is equal to dot3MauType10GigBaseW or any other 10GBASE-W variant -- then the agent MUST also support the Ethernet WAN Interface Sublayer (WIS) MIB [RFC3637] and must follow the interface layering model specified therein. In that case the value of the object ifMauIfIndex is the same as the value of 'ifIndex' for the layer at the top of the stack, i.e., for the ifTable entry that has 'ifType' equal to ethernetCsmacd(6). If the interface-MAU related objects are used to manage a PHY that allows the MAU type to be changed dynamically, then the agent SHALL create ifTable, ifStackTable, and ifInvStackTable entries that pertain to the WIS when ifMauDefaultType is changed to a 10GBASEW variant (i.e., one of dot3MauType10GigBaseW, dot3MauType10GigBaseEW, dot3MauType10GigBaseLW, or dot3MauType10GigBaseSW) from any other type, and shall destroy the WIS-related entries when ifMauDefaultType is changed to a non- 10GBASE-W type. The agent SHALL also change the values of 'ifConnectorPresent' and 'ifHighSpeed' in the ifTable entry indexed by ifMauIfIndex as specified in [RFC3635] and [RFC3637] when ifMauDefaultType is manipulated in this way, but SHALL NOT otherwise alter that entry.

(Note that repeater ports are not represented as interfaces in the Interface MIB.)

3.2.2. Relationship to the 802.3 Repeater MIB Module

The section of this document that defines repeater MAU-related objects specifies an extension to the 802.3 Repeater MIB defined in [RFC2108]. An agent implementing these repeater-MAU related objects MUST also comply with the snmpRptrModCompl compliance statement of the 802.3 Repeater MIB module.

The values of 'rpMauGroupIndex' and 'rpMauPortIndex' used to instantiate a repeater MAU variable SHALL be the same as the values of 'rptrPortGroupIndex' and 'rptrPortIndex' used to instantiate the port that the given MAU is connected to.

3.3. Management of Internal MAUs

In some situations, a MAU can be "internal" -- i.e., its functionality is implemented entirely within a device. For example, a managed repeater may contain an internal repeater-MAU and/or an internal interface-MAU through which management communications originating on one of the repeater's external ports pass, in order to reach the management agent associated with the repeater. Such internal MAUs may or may not be managed. If they are managed, objects describing their attributes should appear in the appropriate MIB subtree: dot3RpMauBasicGroup for internal repeater-MAUs and dot3IfMauBasicGroup for internal interface-MAUs.

3.4. Mapping of IEEE 802.3 Managed Objects

This section contains the mapping between relevant managed objects (attributes) defined in [IEEE802.3] Clause 30, and managed objects defined in this document.

IEEE 802.3 Managed Object	Corresponding SNMP Object
oMAU	
.aMAUID	rpMauIndex or ifMauIndex or broadMauIndex
.aMAUType	rpMauType or ifMauType
.aMAUTypeList	ifMauTypeListBits
.aMediaAvailable	rpMauMediaAvailable or ifMauMediaAvailable
.aLoseMediaCounter	rpMauMediaAvailableStateExits or ifMauMediaAvailableStateExits
.aJabber	rpMauJabberState and rpMauJabberingStateEnters or ifMauJabberState and ifMauJabberingStateEnters
.aMAUAdminState	rpMauStatus or ifMauStatus
.aBbMAUXmitRcvSplitType	broadMauXmtRcvSplitType
.aBroadbandFrequencies	broadMauXmtCarrierFreq and broadMauTranslationFreq
.aFalseCarriers	rpMauFalseCarriers or ifMauFalseCarriers
.acResetMAU	rpMauStatus or ifMauStatus
.acMAUAdminControl	rpMauStatus or ifMauStatus
.nJabber	rpMauJabberTrap or ifMauJabberTrap
oAutoNegotiation	
.aAutoNegID	ifMauIndex
.aAutoNegAdminState	ifMauAutoNegAdminStatus
.aAutoNegRemoteSignalling	ifMauAutoNegRemoteSignalling

.aAutoNegAutoConfig	ifMauAutoNegConfig	
+-----+-----+	+-----+-----+	+-----+-----+
.aAutoNegLocalTechnologyAbility	ifMauAutoNegCapabilityBits	
+-----+-----+	+-----+-----+	+-----+-----+
.aAutoNegAdvertisedTechnologyAbility	ifMauAutoNegAdvertisedBits and ifMauAutoNegRemoteFaultAdverti sed	
+-----+-----+	+-----+-----+	+-----+-----+
.aAutoNegReceivedTechnologyAbili ty	ifMauAutoNegReceivedBits and ifMauAutoNegRemoteFaultReceive d	
+-----+-----+	+-----+-----+	+-----+-----+
.acAutoNegRestartAutoConfig	ifMauAutoNegRestart	
+-----+-----+	+-----+-----+	+-----+-----+
.acAutoNegAdminControl	ifMauAutoNegAdminStatus	
+-----+-----+	+-----+-----+	+-----+-----+

Table 1: Mapping of IEEE 802.3 Managed Objects

The following IEEE 802.3 managed objects have not been included in the MAU-MIB for the following reasons.

+-----+-----+	+-----+-----+	+-----+-----+
IEEE 802.3 Managed Object	Reason for exclusion	
+-----+-----+	+-----+-----+	+-----+-----+
oMAU		
+-----+-----+	+-----+-----+	+-----+-----+
.aIdleErrorCount	Only useful for 100BaseT2, which is not widely implemented.	
+-----+-----+	+-----+-----+	+-----+-----+
oAutoNegotiation		
+-----+-----+	+-----+-----+	+-----+-----+
.aAutoNegLocalSelectorAbility	Only needed for support of isoethernet (802.9a), which is not supported by MAU-MIB.	
+-----+-----+	+-----+-----+	+-----+-----+
.aAutoNegAdvertisedSelectorAbility		
+-----+-----+	+-----+-----+	+-----+-----+
.aAutoNegReceivedSelectorAbility		
+-----+-----+	+-----+-----+	+-----+-----+

Table 2: Unmapped IEEE 802.3 Managed Objects

3.5. Addition of New MAU Types

3.5.1. dot3MauType OBJECT-IDENTITIES

The dot3MauType OBJECT IDENTIFIER and its OBJECT-IDENTITY definitions has been moved from the MAU-MIB into the IANA-maintained IANA-MAU-MIB, the first version of which is defined in this document.

When a new IEEE 802.3 MAU is defined, IANA can re-issue a version of IANA-MAU-MIB with the new dot3MauType OBJECT-IDENTITY and its matching IANAifMauTypeListBits textual convention value and, possibly, with new IANAifMauMediaAvailable, IANAifMauAutoNegCapBits, and/or IANAifJackType values.

An Expert Review, as defined in RFC 2434 [RFC2434], is REQUIRED for the addition of the new MAU, Media Available states, Auto Negotiation capabilities, and/or Jack types.

In some cases, new MAU types may require additional managed objects or may have side effects on the behavior of existing managed objects. In such cases a standards-track specification (which may be a new document or a revision of this document) is also REQUIRED. Any such document is REQUIRED to note any special properties of the MAU types that it defines - for example, side effects on the ifStackTable as noted in this document for 10GBASE-W MAUs.

3.5.2. IANAifMauTypeListBits TEXTUAL-CONVENTION

The syntax of ifMauTypeListBits is changed to be a textual convention, such that the enumerated integer values are now defined in the textual convention IANAifMauTypeListBits, which can be re-specified (with additional values, when defined by IEEE 802.3) in the IANA-maintained MIB module without issuing a new version of this document.

3.5.3. IANAifMauMediaAvailable TEXTUAL-CONVENTION

The syntax of ifMauMediaAvailable and rpMauMediaAvailable is changed to be a textual convention, such that the enumerated integer values are now defined in the textual convention IANAifMauMediaAvailable, which can be re-specified (with additional values, when defined by IEEE 802.3) in the IANA-maintained MIB module without issuing a new version of this document.

3.5.4. IANAifMauAutoNegCapBits TEXTUAL-CONVENTION

The syntax of ifMauAutoNegCapabilityBits, ifMauAutoNegCapAdvertisedBits, and ifMauAutoNegCapReceivedBits objects is changed to be a textual convention, such that the enumerated integer values are now defined in the textual convention IANAifMauAutoNegCapBits, which can be re-specified (with additional values, when defined by IEEE 802.3) in the IANA-maintained MIB module without issuing a new version of this document.

3.5.5. JackType TEXTUAL-CONVENTION

The JackType Textual Convention has been deprecated in favor of the IANAifJackType defined in the IANA-maintained MIB module, so the new Jack types can be added (when defined by IEEE 802.3) without issuing a new version of this document.

4. MAU MIB Definitions

```
MAU-MIB DEFINITIONS ::= BEGIN
```

IMPORTS

```
Counter32, Integer32, Counter64,
OBJECT-TYPE, MODULE-IDENTITY, NOTIFICATION-TYPE, mib-2
FROM SNMPv2-SMI -- RFC 2578
TruthValue, AutonomousType, TEXTUAL-CONVENTION
FROM SNMPv2-TC -- RFC 2579
OBJECT-GROUP, MODULE-COMPLIANCE, NOTIFICATION-GROUP
FROM SNMPv2-CONF -- RFC 2580
InterfaceIndex
FROM IF-MIB -- RFC 2863
IANAifMauTypeListBits, IANAifMauMediaAvailable,
IANAifMauAutoNegCapBits, IANAifJackType
FROM IANA-MAU-MIB
-- http://www.iana.org/assignments/ianamau-mib
;
```

mauMod MODULE-IDENTITY

```
LAST-UPDATED "200704210000Z" -- April 21, 2007
ORGANIZATION "IETF Ethernet Interfaces and Hub MIB Working Group"
CONTACT-INFO
  "WG charter:
   http://www.ietf.org/html.charters/hubmib-charter.html
```

Mailing Lists:

```
General Discussion: hubmib@ietf.org
To Subscribe: hubmib-request@ietf.org
In Body: subscribe your_email_address
```

Chair: Bert Wijnen
Postal: Alcatel-Lucent
Schagen 33
3461 GL Linschoten
Netherlands
Phone: +31-348-407-775
EMail: bwijnen@alcatel-lucent.com

Editor: Edward Beili
Postal: Actelis Networks Inc.
25 Bazel St., P.O.B. 10173
Petach-Tikva 10173
Israel
Tel: +972-3-924-3491
EMail: edward.beili@actelis.com"

DESCRIPTION

"Management information for 802.3 MAUs.

The following reference is used throughout this MIB module:

[IEEE802.3] refers to:

IEEE Std 802.3, 2005 Edition: 'IEEE Standard for Information technology - Telecommunications and information exchange between systems - Local and metropolitan area networks - Specific requirements - Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications'.

Of particular interest is Clause 30, 'Management'.

Copyright (C) The IETF Trust (2007).

This version of this MIB module is part of RFC 4836;
see the RFC itself for full legal notices."

REVISION "200704210000Z" -- April 21, 2007

DESCRIPTION "Updated to reference IANA maintained textual conventions for MAU types, Media Availability state, Auto Negotiation capabilities, and jack types, instead of using internally defined values.

This version is published as RFC 4836."

REVISION "200309190000Z" -- September 19, 2003

DESCRIPTION "Updated to include support for 10 Gb/s MAUs.
This resulted in the following revisions:
- Added OBJECT-IDENTITY definitions for
10 gigabit MAU types

- Added fiberLC jack type to JackType TC
- Extended ifMauTypeListBits with bits for the 10 gigabit MAU types
- Added enumerations to ifMauMediaAvailable, and updated its DESCRIPTION to reflect behaviour at 10 Gb/s
- Added 64-bit version of ifMauFalseCarriers and added mauIfGrpHCStats object group to contain the new object
- Deprecated mauModIfCompl2 and replaced it with mauModIfCompl3, which includes the new object group

This version published as RFC 3636."

REVISION "199908240400Z" -- August 24, 1999
 DESCRIPTION "This version published as RFC 2668. Updated to include support for 1000 Mb/sec MAUs and flow control negotiation."

REVISION "199710310000Z" -- October 31, 1997
 DESCRIPTION "Version published as RFC 2239."

REVISION "199309300000Z" -- September 30, 1993
 DESCRIPTION "Initial version, published as RFC 1515."

::= { snmpDot3MauMgt 6 }

snmpDot3MauMgt OBJECT IDENTIFIER ::= { mib-2 26 }

-- Textual Conventions

JackType ::= TEXTUAL-CONVENTION

STATUS deprecated

DESCRIPTION "***** THIS TC IS DEPRECATED *****"

This TC has been deprecated in favour of IANAifJackType.

Common enumeration values for repeater and interface MAU jack types."

SYNTAX INTEGER {
 other(1),
 rj45(2),
 rj45S(3), -- rj45 shielded
 db9(4),
 bnc(5),
 FAUI(6), -- female aui

```

        mAU1(7), -- male aui
        fiberSC(8),
        fiberMIC(9),
        fiberST(10),
        telco(11),
        mtrj(12), -- fiber MT-RJ
        hssdc(13), -- fiber channel style-2
        fiberLC(14)
    }

dot3RpMauBasicGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 1 }
dot3IfMauBasicGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 2 }
dot3BroadMauBasicGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 3 }

-- OIDs under the following branch are reserved for
-- the IANA-MAU-MIB to assign as MAU type values:
--
--     { snmpDot3MauMgt 4 }

dot3IfMauAutoNegGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 5 }

-- the following OID is the MODULE-IDENTITY value
-- for this MIB module: { snmpDot3MauMgt 6 }

--
-- The Basic Repeater MAU Table
--

rpMauTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF RpMauEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION "Table of descriptive and status information
                about the MAU(s) attached to the ports of a
                repeater."
    ::= { dot3RpMauBasicGroup 1 }

rpMauEntry OBJECT-TYPE
    SYNTAX      RpMauEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION "An entry in the table, containing information
                about a single MAU."
    INDEX       { rpMauGroupIndex,
                rpMauPortIndex,

```

```

        rpMauIndex
    }
    ::= { rpMauTable 1 }

RpMauEntry ::=
    SEQUENCE {
        rpMauGroupIndex          Integer32,
        rpMauPortIndex           Integer32,
        rpMauIndex                Integer32,
        rpMauType                 AutonomousType,
        rpMauStatus               INTEGER,
        rpMauMediaAvailable       IANAifMauMediaAvailable,
        rpMauMediaAvailableStateExits Counter32,
        rpMauJabberState          INTEGER,
        rpMauJabberingStateEnters Counter32,
        rpMauFalseCarriers        Counter32
    }

rpMauGroupIndex OBJECT-TYPE
    SYNTAX      Integer32 (1..2147483647)
    MAX-ACCESS  read-only -- read-only since originally an
                        -- SMIV1 index
    STATUS      current
    DESCRIPTION "This variable uniquely identifies the group
                containing the port to which the MAU described
                by this entry is connected."

    Note: In practice, a group will generally be
    a field-replaceable unit (i.e., module, card,
    or board) that can fit in the physical system
    enclosure, and the group number will correspond
    to a number marked on the physical enclosure.

    The group denoted by a particular value of this
    object is the same as the group denoted by the
    same value of rpPtrGroupIndex."
    REFERENCE   "RFC 2108, rpPtrGroupIndex."
    ::= { rpMauEntry 1 }

rpMauPortIndex OBJECT-TYPE
    SYNTAX      Integer32 (1..2147483647)
    MAX-ACCESS  read-only -- read-only since originally an
                        -- SMIV1 index
    STATUS      current
    DESCRIPTION "This variable uniquely identifies the repeater
                port within group rpMauGroupIndex to which the
                MAU described by this entry is connected."
    REFERENCE   "RFC 2108, rpPtrPortIndex."

```

```
::= { rpMauEntry 2 }
```

rpMauIndex OBJECT-TYPE

```
SYNTAX      Integer32 (1..2147483647)
MAX-ACCESS  read-only -- read-only since originally an
                        -- SMIV1 index

STATUS      current
DESCRIPTION "This variable uniquely identifies the MAU
            described by this entry from among other
            MAUs connected to the same port
            (rpMauPortIndex)."
```

REFERENCE "[IEEE802.3], 30.5.1.1.1, aMAUID."

```
::= { rpMauEntry 3 }
```

rpMauType OBJECT-TYPE

```
SYNTAX      AutonomousType
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION "This object identifies the MAU type. Values for
            standard IEEE 802.3 MAU types are defined in the
            IANA maintained IANA-MAU-MIB module, as
            OBJECT-IDENTITIES of dot3MauType.
            If the MAU type is unknown, the object identifier
            zeroDotZero is returned."
```

REFERENCE "[IEEE802.3], 30.5.1.1.2, aMAUType."

```
::= { rpMauEntry 4 }
```

rpMauStatus OBJECT-TYPE

```
SYNTAX      INTEGER {
                    other(1),
                    unknown(2),
                    operational(3),
                    standby(4),
                    shutdown(5),
                    reset(6)
                }
```

```
MAX-ACCESS  read-write
```

```
STATUS      current
```

```
DESCRIPTION "The current state of the MAU. This object MAY
            be implemented as a read-only object by those
            agents and MAUs that do not implement software
            control of the MAU state. Some agents may not
            support setting the value of this object to some
            of the enumerated values.
```

The value other(1) is returned if the MAU is in a state other than one of the states 2 through 6.

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized.

A MAU in the operational(3) state is fully functional; it operates, and passes signals to its attached DTE or repeater port in accordance to its specification.

A MAU in standby(4) state forces DI and CI to idle, and the media transmitter to idle or fault, if supported. Standby(4) mode only applies to link type MAUs. The state of rpMauMediaAvailable is unaffected.

A MAU in shutdown(5) state assumes the same condition on DI, CI, and the media transmitter, as though it were powered down or not connected. The MAU MAY return other(1) value for the rpMauJabberState and rpMauMediaAvailable objects when it is in this state. For an AUI, this state will remove power from the AUI.

Setting this variable to the value reset(6) resets the MAU in the same manner as a power-off, power-on cycle of at least one-half second would. The agent is not required to return the value reset(6).

Setting this variable to the value operational(3), standby(4), or shutdown(5) causes the MAU to assume the respective state, except that setting a mixing-type MAU or an AUI to standby(4) will cause the MAU to enter the shutdown state."

REFERENCE "[IEEE802.3], 30.5.1.1.7, aMAUAdminState, 30.5.1.2.2, acMAUAdminControl, and 30.5.1.2.1, acResetMAU."
 ::= { rpMauEntry 5 }

rpMauMediaAvailable OBJECT-TYPE

SYNTAX IANAifMauMediaAvailable

MAX-ACCESS read-only

STATUS current

DESCRIPTION "This object identifies Media Available state of the MAU, complementary to the rpMauStatus. Values for the standard IEEE 802.3 Media Available states are defined in the IANA maintained IANA-MAU-MIB

module, as IANAifMauMediaAvailable TC."
 REFERENCE "[IEEE802.3], 30.5.1.1.4, aMediaAvailable."
 ::= { rpMauEntry 6 }

rpMauMediaAvailableStateExits OBJECT-TYPE

SYNTAX Counter32
 MAX-ACCESS read-only
 STATUS current
 DESCRIPTION "A count of the number of times that
 rpMauMediaAvailable for this MAU instance leaves
 the state available(3)."

Discontinuities in the value of this counter can
 occur at re-initialization of the management
 system and at other times, as indicated by the
 value of rpPtrMonitorPortLastChange."

REFERENCE "[IEEE802.3], 30.5.1.1.5, aLoseMediaCounter.
 RFC 2108, rpPtrMonitorPortLastChange"
 ::= { rpMauEntry 7 }

rpMauJabberState OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 unknown(2),
 noJabber(3),
 jabbering(4)
 }

MAX-ACCESS read-only
 STATUS current

DESCRIPTION "The value other(1) is returned if the jabber
 state is not 2, 3, or 4. The agent MUST always
 return other(1) for MAU type dot3MauTypeAUI."

The value unknown(2) is returned when the MAU's
 true state is unknown; for example, when it is
 being initialized.

If the MAU is not jabbering the agent returns
 noJabber(3). This is the 'normal' state.

If the MAU is in jabber state the agent returns
 the jabbering(4) value."

REFERENCE "[IEEE802.3], 30.5.1.1.6, aJabber.jabberFlag."
 ::= { rpMauEntry 8 }

rpMauJabberingStateEnters OBJECT-TYPE

SYNTAX Counter32
 MAX-ACCESS read-only

STATUS current

DESCRIPTION "A count of the number of times that mauJabberState for this MAU instance enters the state jabbering(4). For MAUs of type dot3MauTypeAUI, dot3MauType100BaseT4, dot3MauType100BaseTX, dot3MauType100BaseFX, and all 1000Mbps types, this counter will always indicate zero.

Discontinuities in the value of this counter can occur at re-initialization of the management system and at other times, as indicated by the value of rpPtrMonitorPortLastChange."

REFERENCE "[IEEE802.3], 30.5.1.1.6, aJabber.jabberCounter. RFC 2108, rpPtrMonitorPortLastChange"

::= { rpMauEntry 9 }

rpMauFalseCarriers OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A count of the number of false carrier events during IDLE in 100BASE-X links. This counter does not increment at the symbol rate. It can increment after a valid carrier completion at a maximum rate of once per 100 ms until the next carrier event.

This counter increments only for MAUs of type dot3MauType100BaseT4, dot3MauType100BaseTX, dot3MauType100BaseFX, and all 1000Mbps types.

For all other MAU types, this counter will always indicate zero.

The approximate minimum time for rollover of this counter is 7.4 hours.

Discontinuities in the value of this counter can occur at re-initialization of the management system and at other times, as indicated by the value of rpPtrMonitorPortLastChange."

REFERENCE "[IEEE802.3], 30.5.1.1.10, aFalseCarriers. RFC 2108, rpPtrMonitorPortLastChange"

::= { rpMauEntry 10 }

-- The rpJackTable applies to MAUs attached to repeaters
 -- which have one or more external jacks (connectors).

```
rpJackTable OBJECT-TYPE
    SYNTAX          SEQUENCE OF RpJackEntry
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION     "Information about the external jacks attached
                     to MAUs attached to the ports of a repeater."
    ::= { dot3RpMauBasicGroup 2 }
```

```
rpJackEntry OBJECT-TYPE
    SYNTAX          RpJackEntry
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION     "An entry in the table, containing information
                     about a particular jack."
    INDEX           { rpMauGroupIndex,
                     rpMauPortIndex,
                     rpMauIndex,
                     rpJackIndex
                     }
    ::= { rpJackTable 1 }
```

```
RpJackEntry ::=
    SEQUENCE {
        rpJackIndex          Integer32,
        rpJackType           IANAifJackType
    }
```

```
rpJackIndex OBJECT-TYPE
    SYNTAX          Integer32 (1..2147483647)
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION     "This variable uniquely identifies the jack
                     described by this entry from among other jacks
                     attached to the same MAU (rpMauIndex)."
    ::= { rpJackEntry 1 }
```

```
rpJackType OBJECT-TYPE
    SYNTAX          IANAifJackType
    MAX-ACCESS      read-only
    STATUS          current
    DESCRIPTION     "The jack connector type, as it appears on the
                     outside of the system."
    ::= { rpJackEntry 2 }
```

```
--
-- The Basic Interface MAU Table
--
```

```

ifMauTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IfMauEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION "Table of descriptive and status information
                about MAU(s) attached to an interface."
    ::= { dot3IfMauBasicGroup 1 }

ifMauEntry OBJECT-TYPE
    SYNTAX      IfMauEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION "An entry in the table, containing information
                about a single MAU."
    INDEX       { ifMauIfIndex,
                  ifMauIndex
                }
    ::= { ifMauTable 1 }

IfMauEntry ::=
    SEQUENCE {
        ifMauIfIndex          InterfaceIndex,
        ifMauIndex            Integer32,
        ifMauType             AutonomousType,
        ifMauStatus           INTEGER,
        ifMauMediaAvailable   IANAifMauMediaAvailable,
        ifMauMediaAvailableStateExits Counter32,
        ifMauJabberState      INTEGER,
        ifMauJabberingStateEnters Counter32,
        ifMauFalseCarriers    Counter32,
        ifMauTypeList         Integer32,
        ifMauDefaultType      AutonomousType,
        ifMauAutoNegSupported  TruthValue,
        ifMauTypeListBits     IANAifMauTypeListBits,
        ifMauHCFFalseCarriers Counter64
    }

ifMauIfIndex OBJECT-TYPE
    SYNTAX      InterfaceIndex
    MAX-ACCESS  read-only -- read-only since originally an
                        -- SMIV1 index
    STATUS      current
    DESCRIPTION "This variable uniquely identifies the interface
                to which the MAU described by this entry is
                connected."
    REFERENCE   "RFC 2863, ifIndex"
    ::= { ifMauEntry 1 }

```

```
ifMauIndex OBJECT-TYPE
    SYNTAX      Integer32 (1..2147483647)
    MAX-ACCESS  read-only -- read-only since originally an
                        -- SMIV1 index
    STATUS      current
    DESCRIPTION  "This variable uniquely identifies the MAU
                  described by this entry from among other MAUs
                  connected to the same interface (ifMauIfIndex)."
```

REFERENCE "[IEEE802.3], 30.5.1.1.1, aMAUID."

```
 ::= { ifMauEntry 2 }
```

```
ifMauType OBJECT-TYPE
    SYNTAX      AutonomousType
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION  "This object identifies the MAU type. Values for
                  standard IEEE 802.3 MAU types are defined in the
                  IANA maintained IANA-MAU-MIB module, as
                  OBJECT-IDENTITIES of dot3MauType.
                  If the MAU type is unknown, the object identifier
                  zeroDotZero is returned."
```

This object represents the operational type of the MAU, as determined by either 1) the result of the auto-negotiation function or 2) if auto-negotiation is not enabled or is not implemented for this MAU, by the value of the object ifMauDefaultType. In case 2), a set to the object ifMauDefaultType will force the MAU into the new operating mode."

```
REFERENCE "[IEEE802.3], 30.5.1.1.2, aMAUType."
 ::= { ifMauEntry 3 }
```

```
ifMauStatus OBJECT-TYPE
    SYNTAX      INTEGER {
                    other(1),
                    unknown(2),
                    operational(3),
                    standby(4),
                    shutdown(5),
                    reset(6)
                }
    MAX-ACCESS  read-write
    STATUS      current
    DESCRIPTION  "The current state of the MAU. This object MAY
                  be implemented as a read-only object by those
                  agents and MAUs that do not implement software
                  control of the MAU state. Some agents may not
```

support setting the value of this object to some of the enumerated values.

The value other(1) is returned if the MAU is in a state other than one of the states 2 through 6.

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized.

A MAU in the operational(3) state is fully functional; it operates, and passes signals to its attached DTE or repeater port in accordance to its specification.

A MAU in standby(4) state forces DI and CI to idle and the media transmitter to idle or fault, if supported. Standby(4) mode only applies to link type MAUs. The state of ifMauMediaAvailable is unaffected.

A MAU in shutdown(5) state assumes the same condition on DI, CI, and the media transmitter, as though it were powered down or not connected. The MAU MAY return other(1) value for the ifMauJabberState and ifMauMediaAvailable objects when it is in this state. For an AUI, this state will remove power from the AUI.

Setting this variable to the value reset(6) resets the MAU in the same manner as a power-off, power-on cycle of at least one-half second would. The agent is not required to return the value reset(6).

Setting this variable to the value operational(3), standby(4), or shutdown(5) causes the MAU to assume the respective state, except that setting a mixing-type MAU or an AUI to standby(4) will cause the MAU to enter the shutdown state."

REFERENCE "[IEEE802.3], 30.5.1.1.7, aMAUAdminState, 30.5.1.2.2, acMAUAdminControl, and 30.5.1.2.1, acResetMAU."
 ::= { ifMauEntry 4 }

ifMauMediaAvailable OBJECT-TYPE

```

SYNTAX      IANAifMauMediaAvailable
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION  "This object identifies Media Available state of
              the MAU, complementary to the ifMauStatus. Values
              for the standard IEEE 802.3 Media Available states
              are defined in the IANA maintained IANA-MAU-MIB
              module, as IANAifMauMediaAvailable TC."
REFERENCE   "[IEEE802.3], 30.5.1.1.4, aMediaAvailable."
 ::= { ifMauEntry 5 }

```

ifMauMediaAvailableStateExits OBJECT-TYPE

```

SYNTAX      Counter32
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION  "A count of the number of times that
              ifMauMediaAvailable for this MAU instance leaves
              the state available(3).

              Discontinuities in the value of this counter can
              occur at re-initialization of the management
              system and at other times, as indicated by the
              value of ifCounterDiscontinuityTime."
REFERENCE   "[IEEE802.3], 30.5.1.1.5, aLoseMediaCounter.
              RFC 2863, ifCounterDiscontinuityTime."
 ::= { ifMauEntry 6 }

```

ifMauJabberState OBJECT-TYPE

```

SYNTAX      INTEGER {
                    other(1),
                    unknown(2),
                    noJabber(3),
                    jabbering(4)
                }
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION  "The value other(1) is returned if the jabber
              state is not 2, 3, or 4. The agent MUST always
              return other(1) for MAU type dot3MauTypeAUI.

```

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized.

If the MAU is not jabbering the agent returns noJabber(3). This is the 'normal' state.

If the MAU is in jabber state the agent returns

the jabbering(4) value."
 REFERENCE "[IEEE802.3], 30.5.1.1.6, aJabber.jabberFlag."
 ::= { ifMauEntry 7 }

ifMauJabberingStateEnters OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A count of the number of times that mauJabberState for this MAU instance enters the state jabbering(4). This counter will always indicate zero for MAUs of type dot3MauTypeAUI and those of speeds above 10Mbps.

Discontinuities in the value of this counter can occur at re-initialization of the management system and at other times, as indicated by the value of ifCounterDiscontinuityTime."

REFERENCE "[IEEE802.3], 30.5.1.1.6, aJabber.jabberCounter. RFC 2863, ifCounterDiscontinuityTime."

::= { ifMauEntry 8 }

ifMauFalseCarriers OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A count of the number of false carrier events during IDLE in 100BASE-X and 1000BASE-X links.

For all other MAU types, this counter will always indicate zero. This counter does not increment at the symbol rate.

It can increment after a valid carrier completion at a maximum rate of once per 100 ms for 100BASE-X and once per 10us for 1000BASE-X until the next CarrierEvent.

This counter can roll over very quickly. A management station is advised to poll the ifMauHCFALSECarriers instead of this counter in order to avoid loss of information.

Discontinuities in the value of this counter can occur at re-initialization of the management system and at other times, as indicated by the value of ifCounterDiscontinuityTime."

REFERENCE "[IEEE802.3], 30.5.1.1.10, aFalseCarriers.


```

RFC 2863, ifCounterDiscontinuityTime."
 ::= { ifMauEntry 9 }

```

```

ifMauTypeList OBJECT-TYPE
    SYNTAX      Integer32
    MAX-ACCESS  read-only
    STATUS      deprecated
    DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

```

This object has been deprecated in favour of ifMauTypeListBits.

A value that uniquely identifies the set of possible IEEE 802.3 types that the MAU could be. The value is a sum that initially takes the value zero. Then, for each type capability of this MAU, 2 raised to the power noted below is added to the sum. For example, a MAU that has the capability to be only 10BASE-T would have a value of 512 (2^{*9}). In contrast, a MAU that supports both 10Base-T (full duplex) and 100BASE-TX (full duplex) would have a value of $((2^{*11}) + (2^{*16}))$, or 67584.

The powers of 2 assigned to the capabilities are these:

Power	Capability
0	other or unknown
1	AUI
2	10BASE-5
3	FOIRL
4	10BASE-2
5	10BASE-T duplex mode unknown
6	10BASE-FP
7	10BASE-FB
8	10BASE-FL duplex mode unknown
9	10BROAD36
10	10BASE-T half duplex mode
11	10BASE-T full duplex mode
12	10BASE-FL half duplex mode
13	10BASE-FL full duplex mode
14	100BASE-T4
15	100BASE-TX half duplex mode
16	100BASE-TX full duplex mode
17	100BASE-FX half duplex mode
18	100BASE-FX full duplex mode
19	100BASE-T2 half duplex mode

20 100BASE-T2 full duplex mode

If auto-negotiation is present on this MAU, this object will map to ifMauAutoNegCapability."

::= { ifMauEntry 10 }

ifMauDefaultType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-write

STATUS current

DESCRIPTION "This object identifies the default administrative baseband MAU type to be used in conjunction with the operational MAU type denoted by ifMauType.

The set of possible values for this object is the same as the set defined for the ifMauType object.

This object represents the administratively-configured type of the MAU. If auto-negotiation is not enabled or is not implemented for this MAU, the value of this object determines the operational type of the MAU. In this case, a set to this object will force the MAU into the specified operating mode.

If auto-negotiation is implemented and enabled for this MAU, the operational type of the MAU is determined by auto-negotiation, and the value of this object denotes the type to which the MAU will automatically revert if/when auto-negotiation is later disabled.

NOTE TO IMPLEMENTORS: It may be necessary to provide for underlying hardware implementations which do not follow the exact behavior specified above. In particular, when ifMauAutoNegAdminStatus transitions from enabled to disabled, the agent implementation MUST ensure that the operational type of the MAU (as reported by ifMauType) correctly transitions to the value specified by this object, rather than continuing to operate at the value earlier determined by the auto-negotiation function."

REFERENCE "[IEEE802.3], 30.5.1.1.1, aMAUID, and 22.2.4.1.4."

::= { ifMauEntry 11 }

`ifMauAutoNegSupported OBJECT-TYPE``SYNTAX TruthValue``MAX-ACCESS read-only``STATUS current``DESCRIPTION "This object indicates whether or not
auto-negotiation is supported on this MAU."``::= { ifMauEntry 12 }``ifMauTypeListBits OBJECT-TYPE``SYNTAX IANAifMauTypeListBits``MAX-ACCESS read-only``STATUS current``DESCRIPTION "A value that uniquely identifies the set of
possible IEEE 802.3 types that the MAU could be.
If auto-negotiation is present on this MAU, this
object will map to ifMauAutoNegCapabilityBits.`

Note that this MAU may be capable of operating as a MAU type that is beyond the scope of this MIB. This is indicated by returning the bit value `bOther` in addition to any bit values for standard capabilities that are listed in the `IANAifMauTypeListBits` TC."

`::= { ifMauEntry 13 }``ifMauHCFALSECarriers OBJECT-TYPE``SYNTAX Counter64``MAX-ACCESS read-only``STATUS current``DESCRIPTION "A count of the number of false carrier events
during IDLE in 100BASE-X and 1000BASE-X links.`

For all other MAU types, this counter will always indicate zero. This counter does not increment at the symbol rate.

This counter is a 64-bit version of `ifMauFalseCarriers`. Since the 32-bit version of this counter can roll over very quickly, management stations are advised to poll the 64-bit version instead, in order to avoid loss of information.

Discontinuities in the value of this counter can occur at re-initialization of the management system and at other times, as indicated by the value of `ifCounterDiscontinuityTime`."

`REFERENCE "[IEEE802.3], 30.5.1.1.10, aFalseCarriers.`

```

        RFC 2863, ifCounterDiscontinuityTime."
 ::= { ifMauEntry 14 }

-- The ifJackTable applies to MAUs attached to interfaces
-- which have one or more external jacks (connectors).

ifJackTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IfJackEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION  "Information about the external jacks attached
                  to MAUs attached to an interface."
    ::= { dot3IfMauBasicGroup 2 }

ifJackEntry OBJECT-TYPE
    SYNTAX      IfJackEntry
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION  "An entry in the table, containing information
                  about a particular jack."
    INDEX       { ifMauIfIndex,
                  ifMauIndex,
                  ifJackIndex
                }
    ::= { ifJackTable 1 }

IfJackEntry ::=
    SEQUENCE {
        ifJackIndex      Integer32,
        ifJackType        IANAifJackType
    }

ifJackIndex OBJECT-TYPE
    SYNTAX      Integer32 (1..2147483647)
    MAX-ACCESS   not-accessible
    STATUS       current
    DESCRIPTION  "This variable uniquely identifies the jack
                  described by this entry from among other jacks
                  attached to the same MAU."
    ::= { ifJackEntry 1 }

ifJackType OBJECT-TYPE
    SYNTAX      IANAifJackType
    MAX-ACCESS   read-only
    STATUS       current
    DESCRIPTION  "The jack connector type, as it appears on the
                  outside of the system."
    ::= { ifJackEntry 2 }

```

```
--
-- The MAU Auto-Negotiation Table
--
```

```
ifMauAutoNegTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IfMauAutoNegEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION "Configuration and status objects for the
                auto-negotiation function of MAUs attached to
                interfaces.
```

The ifMauAutoNegTable applies to systems in which auto-negotiation is supported on one or more MAUs attached to interfaces. Note that if auto-negotiation is present and enabled, the ifMauType object reflects the result of the auto-negotiation function."

```
::= { dot3IfMauAutoNegGroup 1 }
```

```
ifMauAutoNegEntry OBJECT-TYPE
    SYNTAX      IfMauAutoNegEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION "An entry in the table, containing configuration
                and status information for the auto-negotiation
                function of a particular MAU."
    INDEX       { ifMauIfIndex,
                  ifMauIndex
                }
    ::= { ifMauAutoNegTable 1 }
```

```
IfMauAutoNegEntry ::=
    SEQUENCE {
        ifMauAutoNegAdminStatus          INTEGER,
        ifMauAutoNegRemoteSignaling      INTEGER,
        ifMauAutoNegConfig                INTEGER,
        ifMauAutoNegCapability            Integer32,
        ifMauAutoNegCapAdvertised         Integer32,
        ifMauAutoNegCapReceived           Integer32,
        ifMauAutoNegRestart               INTEGER,
        ifMauAutoNegCapabilityBits        IANAifMauAutoNegCapBits,
        ifMauAutoNegCapAdvertisedBits     IANAifMauAutoNegCapBits,
        ifMauAutoNegCapReceivedBits       IANAifMauAutoNegCapBits,
        ifMauAutoNegRemoteFaultAdvertised INTEGER,
        ifMauAutoNegRemoteFaultReceived  INTEGER
    }
```

ifMauAutoNegAdminStatus OBJECT-TYPE

SYNTAX INTEGER {
 enabled(1),
 disabled(2)
 }

MAX-ACCESS read-write

STATUS current

DESCRIPTION "Setting this object to enabled(1) will cause the interface that has the auto-negotiation signaling ability to be enabled.

If the value of this object is disabled(2) then the interface will act as it would if it had no auto-negotiation signaling. Under these conditions, an IEEE 802.3 MAU will immediately be forced to the state indicated by the value of the object ifMauDefaultType.

NOTE TO IMPLEMENTORS: When ifMauAutoNegAdminStatus transitions from enabled to disabled, the agent implementation MUST ensure that the operational type of the MAU (as reported by ifMauType) correctly transitions to the value specified by the ifMauDefaultType object, rather than continuing to operate at the value earlier determined by the auto-negotiation function."

REFERENCE "[IEEE802.3], 30.6.1.1.2, aAutoNegAdminState, and 30.6.1.2.2, acAutoNegAdminControl."

::= { ifMauAutoNegEntry 1 }

ifMauAutoNegRemoteSignaling OBJECT-TYPE

SYNTAX INTEGER {
 detected(1),
 notdetected(2)
 }

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A value indicating whether the remote end of the link is using auto-negotiation signaling. It takes the value detected(1) if and only if, during the previous link negotiation, FLP Bursts were received."

REFERENCE "[IEEE802.3], 30.6.1.1.3, aAutoNegRemoteSignaling."

::= { ifMauAutoNegEntry 2 }

ifMauAutoNegConfig OBJECT-TYPE

```

SYNTAX      INTEGER {
                other(1),
                configuring(2),
                complete(3),
                disabled(4),
                parallelDetectFail(5)
            }
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION "A value indicating the current status of the
            auto-negotiation process. The enumeration
            parallelDetectFail(5) maps to a failure in
            parallel detection as defined in 28.2.3.1 of
            [IEEE802.3]."
```

REFERENCE "[IEEE802.3], 30.6.1.1.4, aAutoNegAutoConfig."
::= { ifMauAutoNegEntry 4 }

ifMauAutoNegCapability OBJECT-TYPE

```

SYNTAX      Integer32
MAX-ACCESS  read-only
STATUS      deprecated
DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"
```

This object has been deprecated in favour of
ifMauAutoNegCapabilityBits.

A value that uniquely identifies the set of capabilities of the local auto-negotiation entity. The value is a sum that initially takes the value zero. Then, for each capability of this interface, 2 raised to the power noted below is added to the sum. For example, an interface that has the capability to support only 100Base-TX half duplex would have a value of 32768 (2^{15}). In contrast, an interface that supports both 100Base-TX half duplex and 100Base-TX full duplex would have a value of 98304 ($(2^{15}) + (2^{16})$).

The powers of 2 assigned to the capabilities are these:

Power	Capability
0	other or unknown
(1-9)	(reserved)
10	10BASE-T half duplex mode
11	10BASE-T full duplex mode
12	(reserved)

```

13      (reserved)
14      100BASE-T4
15      100BASE-TX half duplex mode
16      100BASE-TX full duplex mode
17      (reserved)
18      (reserved)
19      100BASE-T2 half duplex mode
20      100BASE-T2 full duplex mode

```

Note that interfaces that support this MIB may have capabilities that extend beyond the scope of this MIB."

```

REFERENCE "[IEEE802.3], 30.6.1.1.5,
          aAutoNegLocalTechnologyAbility."
 ::= { ifMauAutoNegEntry 5 }

```

ifMauAutoNegCapAdvertised OBJECT-TYPE

SYNTAX Integer32

MAX-ACCESS read-write

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

This object has been deprecated in favour of ifMauAutoNegCapAdvertisedBits.

A value that uniquely identifies the set of capabilities advertised by the local auto-negotiation entity. Refer to ifMauAutoNegCapability for a description of the possible values of this object.

Capabilities in this object that are not available in ifMauAutoNegCapability cannot be enabled."

```

REFERENCE "[IEEE802.3], 30.6.1.1.6,
          aAutoNegAdvertisedTechnologyAbility."
 ::= { ifMauAutoNegEntry 6 }

```

ifMauAutoNegCapReceived OBJECT-TYPE

SYNTAX Integer32

MAX-ACCESS read-only

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

This object has been deprecated in favour of ifMauAutoNegCapReceivedBits.

A value that uniquely identifies the set of

capabilities received from the remote auto-negotiation entity. Refer to ifMauAutoNegCapability for a description of the possible values of this object.

Note that interfaces that support this MIB may be attached to remote auto-negotiation entities that have capabilities beyond the scope of this MIB."

REFERENCE "[IEEE802.3], 30.6.1.1.7,
aAutoNegReceivedTechnologyAbility."
::= { ifMauAutoNegEntry 7 }

ifMauAutoNegRestart OBJECT-TYPE

SYNTAX INTEGER {
restart(1),
norestart(2)
}

MAX-ACCESS read-write

STATUS current

DESCRIPTION "If the value of this object is set to restart(1) then this will force auto-negotiation to begin link renegotiation. If auto-negotiation signaling is disabled, a write to this object has no effect.
Setting the value of this object to norestart(2) has no effect."

REFERENCE "[IEEE802.3], 30.6.1.2.1,
acAutoNegRestartAutoConfig."
::= { ifMauAutoNegEntry 8 }

ifMauAutoNegCapabilityBits OBJECT-TYPE

SYNTAX IANAifMauAutoNegCapBits

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A value that uniquely identifies the set of capabilities of the local auto-negotiation entity. Note that interfaces that support this MIB may have capabilities that extend beyond the scope of this MIB.

Note that the local auto-negotiation entity may support some capabilities beyond the scope of this MIB. This is indicated by returning the bit value bOther in addition to any bit values for standard capabilities that are listed in the IANAifMauAutoNegCapBits TC."

REFERENCE "[IEEE802.3], 30.6.1.1.5,
aAutoNegLocalTechnologyAbility."
::= { ifMauAutoNegEntry 9 }

ifMauAutoNegCapAdvertisedBits OBJECT-TYPE

SYNTAX IANAifMauAutoNegCapBits
MAX-ACCESS read-write
STATUS current
DESCRIPTION "A value that uniquely identifies the set of
capabilities advertised by the local
auto-negotiation entity.

Capabilities in this object that are not
available in ifMauAutoNegCapabilityBits cannot
be enabled.

Note that the local auto-negotiation entity may
advertise some capabilities beyond the scope of
this MIB. This is indicated by returning the
bit value bOther in addition to any bit values
for standard capabilities that are listed in the
IANAifMauAutoNegCapBits TC."

REFERENCE "[IEEE802.3], 30.6.1.1.6,
aAutoNegAdvertisedTechnologyAbility."
::= { ifMauAutoNegEntry 10 }

ifMauAutoNegCapReceivedBits OBJECT-TYPE

SYNTAX IANAifMauAutoNegCapBits
MAX-ACCESS read-only
STATUS current
DESCRIPTION "A value that uniquely identifies the set of
capabilities received from the remote
auto-negotiation entity.

Note that interfaces that support this MIB may
be attached to remote auto-negotiation entities
that have capabilities beyond the scope of this
MIB. This is indicated by returning the bit
value bOther in addition to any bit values for
standard capabilities that are listed in the
IANAifMauAutoNegCapBits TC."

REFERENCE "[IEEE802.3], 30.6.1.1.7,
aAutoNegReceivedTechnologyAbility."
::= { ifMauAutoNegEntry 11 }

ifMauAutoNegRemoteFaultAdvertised OBJECT-TYPE

SYNTAX INTEGER {
noError(1),
offline(2),

```

        linkFailure(3),
        autoNegError(4)
    }
MAX-ACCESS read-write
STATUS current
DESCRIPTION "A value that identifies any local fault
indications that this MAU has detected and will
advertise at the next auto-negotiation
interaction for 1000Mbps MAUs."
REFERENCE "[IEEE802.3], 30.6.1.1.6,
aAutoNegAdvertisedTechnologyAbility."
 ::= { ifMauAutoNegEntry 12 }

ifMauAutoNegRemoteFaultReceived OBJECT-TYPE
SYNTAX INTEGER {
    noError(1),
    offline(2),
    linkFailure(3),
    autoNegError(4)
}
MAX-ACCESS read-only
STATUS current
DESCRIPTION "A value that identifies any fault indications
received from the far end of a link by the
local auto-negotiation entity for 1000Mbps
MAUs."
REFERENCE "[IEEE802.3], 30.6.1.1.7,
aAutoNegReceivedTechnologyAbility."
 ::= { ifMauAutoNegEntry 13 }

```

```
--
```

```
-- The Basic Broadband MAU Table
```

```
--
```

```

broadMauBasicTable OBJECT-TYPE
SYNTAX SEQUENCE OF BroadMauBasicEntry
MAX-ACCESS not-accessible
STATUS deprecated
DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

```

This entire table has been deprecated. There have been no reported implementations of this table, and it is unlikely that there ever will be. IEEE recommends that broadband MAU types should not be used for new installations.

Table of descriptive and status information

```

        about the broadband MAUs connected to
        interfaces."
 ::= { dot3BroadMauBasicGroup 1 }

broadMauBasicEntry OBJECT-TYPE
    SYNTAX      BroadMauBasicEntry
    MAX-ACCESS  not-accessible
    STATUS      deprecated
    DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

        An entry in the table, containing information
        about a single broadband MAU."
    INDEX       { broadMauIfIndex,
                  broadMauIndex
                }
 ::= { broadMauBasicTable 1 }

BroadMauBasicEntry ::=
    SEQUENCE {
        broadMauIfIndex      InterfaceIndex,
        broadMauIndex        Integer32,
        broadMauXmtRcvSplitType  INTEGER,
        broadMauXmtCarrierFreq  Integer32,
        broadMauTranslationFreq Integer32
    }

broadMauIfIndex OBJECT-TYPE
    SYNTAX      InterfaceIndex
    MAX-ACCESS  read-only -- read-only since originally an
                          -- SMIV1 index
    STATUS      deprecated
    DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

        This variable uniquely identifies the interface
        to which the MAU described by this entry is
        connected."
    REFERENCE   "RFC 2863, ifIndex."
 ::= { broadMauBasicEntry 1 }

broadMauIndex OBJECT-TYPE
    SYNTAX      Integer32 (1..2147483647)
    MAX-ACCESS  read-only -- read-only since originally an
                          -- SMIV1 index
    STATUS      deprecated
    DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

        This variable uniquely identifies the MAU
        connected to interface broadMauIfIndex that is

```

described by this entry."
 REFERENCE "[IEEE802.3], 30.5.1.1.1, aMAUID."
 ::= { broadMauBasicEntry 2 }

broadMauXmtRcvSplitType OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 single(2),
 dual(3)
 }

MAX-ACCESS read-only

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

This object indicates the type of frequency multiplexing/cabling system used to separate the transmit and receive paths for the 10BROAD36 MAU.

The value other(1) is returned if the split type is not either single or dual.

The value single(2) indicates a single cable system. The value dual(3) indicates a dual cable system, offset normally zero."

REFERENCE "[IEEE802.3], 30.5.1.1.8, aBbMAUXmitRcvSplitType."
 ::= { broadMauBasicEntry 3 }

broadMauXmtCarrierFreq OBJECT-TYPE

SYNTAX Integer32

MAX-ACCESS read-only

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

This variable indicates the transmit carrier frequency of the 10BROAD36 MAU in MHz/4; that is, in units of 250 kHz."

REFERENCE "[IEEE802.3], 30.5.1.1.9,
 aBroadbandFrequencies.xmitCarrierFrequency."
 ::= { broadMauBasicEntry 4 }

broadMauTranslationFreq OBJECT-TYPE

SYNTAX Integer32

MAX-ACCESS read-only

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

This variable indicates the translation offset

```

        frequency of the 10BROAD36 MAU in MHz/4; that
        is, in units of 250 kHz."
REFERENCE    "[IEEE802.3], 30.5.1.1.9,
              aBroadbandFrequencies.translationFrequency."
 ::= { broadMauBasicEntry 5 }

-- Notifications for use by 802.3 MAUs

snmpDot3MauTraps OBJECT IDENTIFIER ::= { snmpDot3MauMgt 0 }

rpMauJabberTrap NOTIFICATION-TYPE
  OBJECTS      { rpMauJabberState }
  STATUS       current
  DESCRIPTION   "This trap is sent whenever a managed repeater
                MAU enters the jabber state.

                The agent MUST throttle the generation of
                consecutive rpMauJabberTraps so that there is at
                least a five-second gap between them."
REFERENCE      "[IEEE802.3], 30.5.1.3.1, nJabber notification."
 ::= { snmpDot3MauTraps 1 }

ifMauJabberTrap NOTIFICATION-TYPE
  OBJECTS      { ifMauJabberState }
  STATUS       current
  DESCRIPTION   "This trap is sent whenever a managed interface
                MAU enters the jabber state.

                The agent MUST throttle the generation of
                consecutive ifMauJabberTraps so that there is at
                least a five-second gap between them."

REFERENCE      "[IEEE802.3], 30.5.1.3.1, nJabber notification."
 ::= { snmpDot3MauTraps 2 }

-- Conformance information

mauModConf
  OBJECT IDENTIFIER ::= { mauMod 1 }
mauModCompls
  OBJECT IDENTIFIER ::= { mauModConf 1 }
mauModObjGrps
  OBJECT IDENTIFIER ::= { mauModConf 2 }
mauModNotGrps
  OBJECT IDENTIFIER ::= { mauModConf 3 }

-- Object groups

```

```
mauRpGrpBasic OBJECT-GROUP
  OBJECTS      { rpMauGroupIndex,
                  rpMauPortIndex,
                  rpMauIndex,
                  rpMauType,
                  rpMauStatus,
                  rpMauMediaAvailable,
                  rpMauMediaAvailableStateExits,
                  rpMauJabberState,
                  rpMauJabberingStateEnters
                }
  STATUS       current
  DESCRIPTION   "Basic conformance group for MAUs attached to
                  repeater ports. This group is also the
                  conformance specification for RFC 1515
                  implementations."
  ::= { mauModObjGrps 1 }

mauRpGrp100Mbps OBJECT-GROUP
  OBJECTS      { rpMauFalseCarriers }
  STATUS       current
  DESCRIPTION   "Conformance group for MAUs attached to
                  repeater ports with 100 Mb/s or greater
                  capability."
  ::= { mauModObjGrps 2 }

mauRpGrpJack OBJECT-GROUP
  OBJECTS      { rpJackType }
  STATUS       current
  DESCRIPTION   "Conformance group for MAUs attached to
                  repeater ports with managed jacks."
  ::= { mauModObjGrps 3 }

mauIfGrpBasic OBJECT-GROUP
  OBJECTS      { ifMauIfIndex,
                  ifMauIndex,
                  ifMauType,
                  ifMauStatus,
                  ifMauMediaAvailable,
                  ifMauMediaAvailableStateExits,
                  ifMauJabberState,
                  ifMauJabberingStateEnters
                }
  STATUS       current
  DESCRIPTION   "Basic conformance group for MAUs attached to
                  interfaces. This group also provides a
                  conformance specification for RFC 1515
                  implementations."
```

```
 ::= { mauModObjGrps 4 }

mauIfGrp100Mbs OBJECT-GROUP
  OBJECTS      { ifMauFalseCarriers,
                  ifMauTypeList,
                  ifMauDefaultType,
                  ifMauAutoNegSupported
                }

  STATUS        deprecated
  DESCRIPTION   "***** THIS GROUP IS DEPRECATED *****

                  Conformance group for MAUs attached to
                  interfaces with 100 Mb/s capability.

                  This object group has been deprecated in favor
                  of mauIfGrpHighCapacity."
  ::= { mauModObjGrps 5 }

mauIfGrpJack OBJECT-GROUP
  OBJECTS      { ifJackType }
  STATUS        current
  DESCRIPTION   "Conformance group for MAUs attached to
                  interfaces with managed jacks."
  ::= { mauModObjGrps 6 }

mauIfGrpAutoNeg OBJECT-GROUP
  OBJECTS      { ifMauAutoNegAdminStatus,
                  ifMauAutoNegRemoteSignaling,
                  ifMauAutoNegConfig,
                  ifMauAutoNegCapability,
                  ifMauAutoNegCapAdvertised,
                  ifMauAutoNegCapReceived,
                  ifMauAutoNegRestart
                }

  STATUS        deprecated
  DESCRIPTION   "***** THIS GROUP IS DEPRECATED *****

                  Conformance group for MAUs attached to
                  interfaces with managed auto-negotiation.

                  This object group has been deprecated in favor
                  of mauIfGrpAutoNeg2."
  ::= { mauModObjGrps 7 }

mauBroadBasic OBJECT-GROUP
  OBJECTS      { broadMauIfIndex,
                  broadMauIndex,
```



```

        broadMauXmtRcvSplitType,
        broadMauXmtCarrierFreq,
        broadMauTranslationFreq
    }
    STATUS      deprecated
    DESCRIPTION  "***** THIS GROUP IS DEPRECATED *****
Conformance group for broadband MAUs attached
to interfaces.

This object group is deprecated.  There have
been no reported implementations of this group,
and it was felt to be unlikely that there will
be any future implementations."
 ::= { mauModObjGrps 8 }

mauIfGrpHighCapacity OBJECT-GROUP
    OBJECTS      { ifMauFalseCarriers,
                    ifMauTypeListBits,
                    ifMauDefaultType,
                    ifMauAutoNegSupported
                }
    STATUS      current
    DESCRIPTION  "Conformance group for MAUs attached to
interfaces with 100 Mb/s or greater capability."
 ::= { mauModObjGrps 9 }

mauIfGrpAutoNeg2 OBJECT-GROUP
    OBJECTS      { ifMauAutoNegAdminStatus,
                    ifMauAutoNegRemoteSignaling,
                    ifMauAutoNegConfig,
                    ifMauAutoNegCapabilityBits,
                    ifMauAutoNegCapAdvertisedBits,
                    ifMauAutoNegCapReceivedBits,
                    ifMauAutoNegRestart
                }
    STATUS      current
    DESCRIPTION  "Conformance group for MAUs attached to
interfaces with managed auto-negotiation."
 ::= { mauModObjGrps 10 }

mauIfGrpAutoNeg1000Mbps OBJECT-GROUP
    OBJECTS      { ifMauAutoNegRemoteFaultAdvertised,
                    ifMauAutoNegRemoteFaultReceived
                }
    STATUS      current
    DESCRIPTION  "Conformance group for 1000Mbps MAUs attached to
interfaces with managed auto-negotiation."
 ::= { mauModObjGrps 11 }

```

```

mauIfGrpHCStats OBJECT-GROUP
    OBJECTS      { ifMauHCFalseCarriers }
    STATUS       current
    DESCRIPTION   "Conformance for high capacity statistics for
                  MAUs attached to interfaces."
    ::= { mauModObjGrps 12 }

-- Notification groups

rpMauNotifications NOTIFICATION-GROUP
    NOTIFICATIONS { rpMauJabberTrap }
    STATUS       current
    DESCRIPTION   "Notifications for repeater MAUs."
    ::= { mauModNotGrps 1 }

ifMauNotifications NOTIFICATION-GROUP
    NOTIFICATIONS { ifMauJabberTrap }
    STATUS       current
    DESCRIPTION   "Notifications for interface MAUs."
    ::= { mauModNotGrps 2 }

-- Compliances

mauModRpCompl MODULE-COMPLIANCE
    STATUS       deprecated
    DESCRIPTION   "***** THIS COMPLIANCE IS DEPRECATED *****
                  Compliance for MAUs attached to repeater
                  ports.

                  This compliance is deprecated and replaced by
                  mauModRpCompl2, which corrects an oversight by
                  allowing rpMauStatus to be implemented
                  read-only."

MODULE -- this module
    MANDATORY-GROUPS { mauRpGrpBasic }

    GROUP      mauRpGrp100Mbs
    DESCRIPTION "Implementation of this optional group is
                recommended for MAUs that have 100Mb/s or
                greater capability."

    GROUP      mauRpGrpJack
    DESCRIPTION "Implementation of this optional group is
                recommended for MAUs that have one or more
                external jacks."

    GROUP      rpMauNotifications

```

```

        DESCRIPTION "Implementation of this group is recommended
                     for MAUs attached to repeater ports."
 ::= { mauModCompls 1 }

mauModIfCompl MODULE-COMPLIANCE
STATUS      deprecated
DESCRIPTION "***** THIS COMPLIANCE IS DEPRECATED *****

        Compliance for MAUs attached to interfaces.
        This compliance is deprecated and replaced by
        mauModIfCompl2."

MODULE -- this module
MANDATORY-GROUPS { mauIfGrpBasic }

GROUP      mauIfGrp100Mbs
DESCRIPTION "Implementation of this optional group is
             recommended for MAUs that have 100Mb/s
             capability."

GROUP      mauIfGrpJack
DESCRIPTION "Implementation of this optional group is
             recommended for MAUs that have one or more
             external jacks."

GROUP      mauIfGrpAutoNeg
DESCRIPTION "Implementation of this group is mandatory
             for MAUs that support managed
             auto-negotiation."

GROUP      mauBroadBasic
DESCRIPTION "Implementation of this group is mandatory
             for broadband MAUs."

GROUP      ifMauNotifications
DESCRIPTION "Implementation of this group is recommended
             for MAUs attached to interfaces."
 ::= { mauModCompls 2 }

mauModIfCompl2 MODULE-COMPLIANCE
STATUS      deprecated
DESCRIPTION "***** THIS COMPLIANCE IS DEPRECATED *****

        Compliance for MAUs attached to interfaces.

        This compliance is deprecated and replaced by
        mauModIfCompl3."

```

```

MODULE -- this module
    MANDATORY-GROUPS { mauIfGrpBasic }

    GROUP          mauIfGrpHighCapacity
    DESCRIPTION    "Implementation of this optional group is
                    recommended for MAUs that have 100Mb/s
                    or greater capability."

    GROUP          mauIfGrpJack
    DESCRIPTION    "Implementation of this optional group is
                    recommended for MAUs that have one or more
                    external jacks."

    GROUP          mauIfGrpAutoNeg2
    DESCRIPTION    "Implementation of this group is mandatory
                    for MAUs that support managed
                    auto-negotiation."

    GROUP          mauIfGrpAutoNeg1000Mbps
    DESCRIPTION    "Implementation of this group is mandatory
                    for MAUs that have 1000Mb/s or greater
                    capability and support managed
                    auto-negotiation."

    GROUP          ifMauNotifications
    DESCRIPTION    "Implementation of this group is recommended
                    for MAUs attached to interfaces."

    OBJECT          ifMauStatus
    MIN-ACCESS      read-only
    DESCRIPTION    "Write access is not required."
 ::= { mauModCompls 3 }

```

mauModRpCompl2 MODULE-COMPLIANCE

```

STATUS      current
DESCRIPTION "Compliance for MAUs attached to repeater
            ports."

```

Note that compliance with this compliance statement requires compliance with the snmpRptrModCompl MODULE-COMPLIANCE statement of the SNMP-REPEATER-MIB (RFC 2108)."

```

MODULE -- this module
    MANDATORY-GROUPS { mauRpGrpBasic }

    GROUP          mauRpGrp100Mbs

```

DESCRIPTION "Implementation of this optional group is recommended for MAUs that have 100Mb/s or greater capability."

GROUP mauRpGrpJack

DESCRIPTION "Implementation of this optional group is recommended for MAUs that have one or more external jacks."

GROUP rpMauNotifications

DESCRIPTION "Implementation of this group is recommended for MAUs attached to repeater ports."

OBJECT rpMauStatus

MIN-ACCESS read-only

DESCRIPTION "Write access is not required."

::= { mauModCompls 4 }

mauModIfCompl3 MODULE-COMPLIANCE

STATUS current

DESCRIPTION "Compliance for MAUs attached to interfaces."

Note that compliance with this compliance statement requires compliance with the ifCompliance3 MODULE-COMPLIANCE statement of the IF-MIB (RFC 2863) and the dot3Compliance2 MODULE-COMPLIANCE statement of the EtherLike-MIB (RFC3635)."

MODULE -- this module

MANDATORY-GROUPS { mauIfGrpBasic }

GROUP mauIfGrpHighCapacity

DESCRIPTION "Implementation of this optional group is recommended for MAUs that have 100Mb/s or greater capability."

GROUP mauIfGrpHCStats

DESCRIPTION "Implementation of this group is mandatory for MAUs that have 1000Mb/s capacity, and is recommended for MAUs that have 100Mb/s capacity."

GROUP mauIfGrpJack

DESCRIPTION "Implementation of this optional group is recommended for MAUs that have one or more external jacks."

```

GROUP      mauIfGrpAutoNeg2
DESCRIPTION "Implementation of this group is mandatory
            for MAUs that support managed
            auto-negotiation."

GROUP      mauIfGrpAutoNeg1000Mbps
DESCRIPTION "Implementation of this group is mandatory
            for MAUs that have 1000Mb/s or greater
            capability and support managed
            auto-negotiation."

GROUP      ifMauNotifications
DESCRIPTION "Implementation of this group is recommended
            for MAUs attached to interfaces."

OBJECT      ifMauStatus
MIN-ACCESS  read-only
DESCRIPTION "Write access is not required."
::= { mauModCompls 5 }

```

END

5. IANA-Maintained MAU TC Definitions

IANA-MAU-MIB DEFINITIONS ::= BEGIN

IMPORTS

```

MODULE-IDENTITY, OBJECT-IDENTITY, mib-2
FROM SNMPv2-SMI
TEXTUAL-CONVENTION
FROM SNMPv2-TC
;

```

ianaMauMIB MODULE-IDENTITY

```

LAST-UPDATED "200704210000Z" -- April 21, 2007
ORGANIZATION "IANA"
CONTACT-INFO "
    Internet Assigned Numbers Authority

    Postal: ICANN
            4676 Admiralty Way, Suite 330
            Marina del Rey, CA 90292

    Tel: +1-310-823-9358
    EMail: iana@iana.org"

```

DESCRIPTION

```

"This MIB module defines dot3MauType OBJECT-IDENTITIES and
IANAifMauListBits, IANAifMauMediaAvailable,
IANAifMauAutoNegCapBits, and IANAifJackType

```

TEXTUAL-CONVENTIONS, specifying enumerated values of the ifMauTypeListBits, ifMauMediaAvailable / rpMauMediaAvailable, ifMauAutoNegCapabilityBits / ifMauAutoNegCapAdvertisedBits / ifMauAutoNegCapReceivedBits and ifJackType / rpJackType objects respectively, defined in the MAU-MIB.

It is intended that each new MAU type, Media Availability state, Auto Negotiation capability and/or Jack type defined by the IEEE 802.3 working group and approved for publication in a revision of IEEE Std 802.3 will be added to this MIB module, provided that it is suitable for being managed by the base objects in the MAU-MIB. An Expert Review, as defined in RFC 2434 [RFC2434], is REQUIRED for such additions.

The following reference is used throughout this MIB module:

[IEEE802.3] refers to:

IEEE Std 802.3, 2005 Edition: 'IEEE Standard for Information technology - Telecommunications and information exchange between systems - Local and metropolitan area networks - Specific requirements - Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications'.

This reference should be updated as appropriate when new MAU types, Media Availability states, Auto Negotiation capabilities, and/or Jack types are added to this MIB module.

Copyright (C) The IETF Trust (2007).

The initial version of this MIB module was published in RFC 4836; for full legal notices see the RFC itself.

Supplementary information may be available at:

<http://www.ietf.org/copyrights/ianamib.html>

```
REVISION      "200704210000Z"  -- April 21, 2007
DESCRIPTION   "Initial version of this MIB as published in
               RFC 4836."
 ::= { mib-2 154 }
```

-- Textual Conventions

IANAifMauTypeListBits ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION

"This data type is used as the syntax of the ifMauTypeListBits object in the (updated) definition of MAU-MIB's ifMauTable.

The most recent version of this textual convention is available in the online version of this MIB module on the IANA web site.

Requests for new values should be made to IANA via email (iana@iana.org).

Note that changes in this textual convention SHALL be synchronized with relevant changes in the dot3MauType OBJECT-IDENTITIES."

REFERENCE

"[IEEE802.3], Section 30.5.1.1.2"

```
SYNTAX      BITS {
    bOther(0),          -- other or unknown
    bAUI(1),            -- AUI
    b10base5(2),        -- 10BASE-5
    bFoirl(3),          -- FOIRL

    b10base2(4),        -- 10BASE-2
    b10baseT(5),        -- 10BASE-T duplex mode unknown
    b10baseFP(6),       -- 10BASE-FP
    b10baseFB(7),       -- 10BASE-FB
    b10baseFL(8),       -- 10BASE-FL duplex mode unknown
    b10broad36(9),      -- 10BROAD36
    b10baseTHD(10),     -- 10BASE-T half duplex mode
    b10baseTFD(11),     -- 10BASE-T full duplex mode
    b10baseFLHD(12),    -- 10BASE-FL half duplex mode
    b10baseFLFD(13),    -- 10BASE-FL full duplex mode
    b100baseT4(14),     -- 100BASE-T4
    b100baseTXHD(15),   -- 100BASE-TX half duplex mode
    b100baseTXFD(16),   -- 100BASE-TX full duplex mode
    b100baseFXHD(17),   -- 100BASE-FX half duplex mode
    b100baseFXFD(18),   -- 100BASE-FX full duplex mode
    b100baseT2HD(19),   -- 100BASE-T2 half duplex mode
    b100baseT2FD(20),   -- 100BASE-T2 full duplex mode

    b1000baseXHD(21),   -- 1000BASE-X half duplex mode
    b1000baseXFD(22),   -- 1000BASE-X full duplex mode
    b1000baseLXHD(23),  -- 1000BASE-LX half duplex mode
    b1000baseLXFD(24),  -- 1000BASE-LX full duplex mode
    b1000baseSXHD(25),  -- 1000BASE-SX half duplex mode
    b1000baseSXFD(26),  -- 1000BASE-SX full duplex mode
    b1000baseCXHD(27),  -- 1000BASE-CX half duplex mode
    b1000baseCXFD(28),  -- 1000BASE-CX full duplex mode
    b1000baseTHD(29),   -- 1000BASE-T half duplex mode
    b1000baseTFD(30),   -- 1000BASE-T full duplex mode

    b10GbaseX(31),      -- 10GBASE-X
    b10GbaseLX4(32),    -- 10GBASE-LX4
```



```

b10GbaseR(33),      -- 10GBASE-R
b10GbaseER(34),     -- 10GBASE-ER
b10GbaseLR(35),     -- 10GBASE-LR
b10GbaseSR(36),     -- 10GBASE-SR
b10GbaseW(37),      -- 10GBASE-W
b10GbaseEW(38),     -- 10GBASE-EW
b10GbaseLW(39),     -- 10GBASE-LW
b10GbaseSW(40),     -- 10GBASE-SW
-- new since RFC 3636
b10GbaseCX4(41),    -- 10GBASE-CX4
b2BaseTL(42),       -- 2BASE-TL
b10PassTS(43),      -- 10PASS-TS
b100BaseBX10D(44),  -- 100BASE-BX10D
b100BaseBX10U(45),  -- 100BASE-BX10U
b100BaseLX10(46),   -- 100BASE-LX10
b1000BaseBX10D(47), -- 1000BASE-BX10D
b1000BaseBX10U(48), -- 1000BASE-BX10U
b1000BaseLX10(49),  -- 1000BASE-LX10
b1000BasePX10D(50), -- 1000BASE-PX10D
b1000BasePX10U(51), -- 1000BASE-PX10U
b1000BasePX20D(52), -- 1000BASE-PX20D
b1000BasePX20U(53)  -- 1000BASE-PX20U
}

```

IANAifMauMediaAvailable ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION

"This data type is used as the syntax of the ifMauMediaAvailable and rpMauMediaAvailable objects in the (updated) definition of MAU-MIB's ifMauTable and rpMauTable respectively.

Possible values are:

other(1)	- undefined (not listed below)
unknown(2)	- MAU's true state is unknown; e.g., during initialization
available(3)	- link, light, or loopback is normal
notAvailable(4)	- link loss, low light, or no loopback
remoteFault(5)	- a fault has been detected at the remote end of the link. This value applies to 10BASE-FB, 100BASE-T4 Far End Fault Indication and non-specified remote faults from a system running auto-negotiation
invalidSignal(6)	- invalid signal has been received from the other end of the link, 10BASE-FB only
remoteJabber(7)	- remote fault, due to jabber

remoteLinkLoss(8)	- remote fault, due to link loss
remoteTest(9)	- remote fault, due to test
offline(10)	- offline, Clause 37 Auto-Negotiation only
autoNegError(11)	- Auto-Negotiation Error, Clause 37 Auto-Negotiation only
pmdLinkFault(12)	- PMA/PMD receive link fault. In case of PAF (2BASE-TL / 10PASS-TS PHYs), all PMEs in the aggregation group have detected a link fault
wisFrameLoss(13)	- WIS loss of frame, 10GBASE-W only
wisSignalLoss(14)	- WIS loss of signal, 10GBASE-W only
pcsLinkFault(15)	- PCS receive link fault
excessiveBER(16)	- PCS Bit Error Ratio monitor reporting excessive error ratio
dxsLinkFault(17)	- DTE XGXS receive link fault, XAUI only
pxsLinkFault(18)	- PHY XGXS receive link fault, XAUI only
availableReduced(19)	- link normal, reduced bandwidth, 2BASE-TL / 10PASS-TS only
ready(20)	- at least one PME in the aggregation group is detecting handshake tones, 2BASE-TL / 10PASS-TS only

If the MAU is a 10M b/s link or fiber type (FOIRL, 10BASE-T, 10BASE-F), then this is equivalent to the link test fail state/low light function. For an AUI, 10BASE2, 10BASE5, or 10BROAD36 MAU, this indicates whether loopback is detected on the DI circuit. The value of this attribute persists between packets for MAU types AUI, 10BASE5, 10BASE2, 10BROAD36, and 10BASEFP.

At power-up or following a reset, the Media Available state will be unknown(2) for AUI, 10BASE5, 10BASE2, 10BROAD36, and 10BASE-FP MAUs. For these MAUs loopback will be tested on each transmission during which no collision is detected.

If DI is receiving input when DO returns to IDL after a transmission and there has been no collision during the transmission, then loopback will be detected. The Media Available state will only change during noncollided transmissions for AUI, 10BASE2, 10BASE5, 10BROAD36, and 10BASE-FP MAUs.

For 100BASE-T2, 100BASE-T4, 100BASE-TX, 100BASE-FX, 100BASE-LX10, and 100BASE-BX10 PHYs the enumerations match the states within the link integrity state diagram. Any MAU that implements management of [IEEE802.3] Clause 28 Auto-Negotiation, will map remote fault indication to remoteFault(5).

Any MAU that implements management of Clause 37 Auto-Negotiation, will map the received RF1 and RF2 bits as follows: Offline maps to offline(10), Link_Failure maps to remoteFault(5), and Auto-Negotiation Error maps to autoNegError(11).

The value remoteFault(5) applies to 10BASE-FB remote fault indication, the 100BASE-X far-end fault indication, and nonspecified remote faults from a system running Clause 28 Auto-Negotiation.

The value remoteJabber(7), remoteLink loss(8), or remoteTest(9) SHOULD be used instead of remoteFault(5) where the reason for remote fault is identified in the remote signaling protocol. Where a Clause 22 MII or Clause 35 GMII is present, a logic one in the remote fault bit maps to the value remoteFault(5), a logic zero in the link status bit maps to the enumeration notAvailable(4). The value notAvailable(4) takes precedence over remoteFault(5).

For 2BASE-TL and 10PASS-TS PHYs, the value unknown(2) maps to the condition where the PHY (PCS with connected PMEs) is initializing, the value ready(20) maps to the condition where the interface is down and at least one PME in the aggregation group is ready for handshake, the value available(3) maps to the condition where all the PMEs in the aggregation group are up, the value notAvailable(4) maps to the condition where all the PMEs in the aggregation group are down and no handshake tones are detected, the value availableReduced(19) maps to the condition where the interface is up, a link fault is detected at the receive direction by one or more PMEs in the aggregation group, but at least one PME is up and the enumeration pmdLinkFault(12) maps to the condition where a link fault is detected at the receive direction by all of the PMEs in the aggregation group.

For 10 Gb/s the enumerations map to value of the link_fault variable within the Link Fault Signaling state diagram as follows: the value OK maps to the value available(3), the value Local Fault maps to the value notAvailable(4), and the value Remote Fault maps to the value remoteFault(5). The value pmdLinkFault(12), wisFrameLoss(13), wisSignalLoss(14), pcsLinkFault(15), excessiveBER(16), or dxsLinkFault(17) SHOULD be used instead of the value notAvailable(4), where the reason for the Local Fault state can be identified through the use of the Clause 45 MDIO Interface. Where multiple reasons for the Local Fault state can be identified, only the highest precedence error SHOULD be

reported. This precedence in descending order is as follows:

```
pxsLinkFault
pmdLinkFault
wisFrameLoss
wisSignalLoss
pcsLinkFault
excessiveBER
dxsLinkFault.
```

Where a Clause 45 MDIO interface is present a logic zero in the PMA/PMD Receive link status bit ([IEEE802.3] Section 45.2.1.2.2) maps to the value pmdLinkFault(12), logic one in the LOF status bit (Section 45.2.2.10.4) maps to the value wisFrameLoss(13), a logic one in the LOS status bit (Section 45.2.2.10.5) maps to the value wisSignalLoss, a logic zero in the PCS Receive link status bit (Section 45.2.3.2.2) maps to the value pcsLinkFault(15), a logic one in the 10GBASE-R PCS Latched high BER status bit (Section 45.2.3.12.2) maps to the value excessiveBER, a logic zero in the DTE XS receive link status bit (Section 45.2.5.2.2) maps to the value dxsLinkFault(17) and a logic zero in the PHY XS transmit link status bit (Section 45.2.4.2.2) maps to the value pxsLinkFault(18).

The most recent version of this textual convention is available in the online version of this MIB module on the IANA web site.

Requests for new values should be made to IANA via email (iana@iana.org)."

REFERENCE

"[IEEE802.3], Section 30.5.1.1.4"

```
SYNTAX          INTEGER {
    other(1),
    unknown(2),
    available(3),
    notAvailable(4),
    remoteFault(5),
    invalidSignal(6),
    remoteJabber(7),
    remoteLinkLoss(8),
    remoteTest(9),
    offline(10),
    autoNegError(11),
    pmdLinkFault(12),
    wisFrameLoss(13),
    wisSignalLoss(14),
    pcsLinkFault(15),
```

```

        excessiveBER(16),
        dxsLinkFault(17),
        pxsLinkFault(18),
        availableReduced(19),
        ready(20)
    }

```

IANAifMauAutoNegCapBits ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION

"This data type is used as the syntax of the ifMauAutoNegCapabilityBits, ifMauAutoNegCapAdvertisedBits, and ifMauAutoNegCapReceivedBits objects in the (updated) definition of MAU-MIB's ifMauAutoNegTable.

The most recent version of this textual convention is available in the online version of this MIB module on the IANA web site.

Requests for new values should be made to IANA via email (iana@iana.org)."

REFERENCE

"[IEEE802.3], Section 30.6.1.1.5"

```

SYNTAX      BITS {
    bOther(0),           -- other or unknown
    b10baseT(1),         -- 10BASE-T half duplex mode
    b10baseTFD(2),       -- 10BASE-T full duplex mode
    b100baseT4(3),       -- 100BASE-T4
    b100baseTX(4),       -- 100BASE-TX half duplex mode
    b100baseTXFD(5),     -- 100BASE-TX full duplex mode
    b100baseT2(6),       -- 100BASE-T2 half duplex mode
    b100baseT2FD(7),     -- 100BASE-T2 full duplex mode
    bFdxPause(8),        -- PAUSE for full-duplex links
    bFdxAPause(9),       -- Asymmetric PAUSE for full-duplex
                        -- links
    bFdxSPause(10),      -- Symmetric PAUSE for full-duplex
                        -- links
    bFdxBPAuse(11),      -- Asymmetric and Symmetric PAUSE for
                        -- full-duplex links
    b1000baseX(12),      -- 1000BASE-X, -LX, -SX, -CX half
                        -- duplex mode
    b1000baseXFD(13),    -- 1000BASE-X, -LX, -SX, -CX full
                        -- duplex mode
    b1000baseT(14),      -- 1000BASE-T half duplex mode
    b1000baseTFD(15)     -- 1000BASE-T full duplex mode
}

```

IANAifJackType ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION

"Common enumeration values for repeater and interface MAU jack types. This data type is used as the syntax of the ifJackType and rpJackType objects in the (updated) definition of MAU-MIB's ifJackTable and rpJackTable respectively.

Possible values are:

other(1)	- undefined or unknown
rj45(2)	- RJ45
rj45S(3)	- RJ45 shielded
db9(4)	- DB9
bnc(5)	- BNC
fAUI(6)	- AUI female
mAUI(7)	- AUI male
fiberSC(8)	- SC fiber
fiberMIC(9)	- MIC fiber
fiberST(10)	- ST fiber
telco(11)	- Telco
mtrj(12)	- MT-RJ fiber
hssdc(13)	- fiber channel style-2
fiberLC(14)	- LC fiber
cx4(15)	- IB4X for 10GBASE-CX4

The most recent version of this textual convention is available in the online version of this MIB module on the IANA web site.

Requests for new values should be made to IANA via email (iana@iana.org)."

```
SYNTAX      INTEGER {
    other(1),
    rj45(2),
    rj45S(3),
    db9(4),
    bnc(5),
    fAUI(6),
    mAUI(7),
    fiberSC(8),
    fiberMIC(9),
    fiberST(10),
    telco(11),
    mtrj(12),
    hssdc(13),
    fiberLC(14),
    -- new since RFC 3636
    cx4(15)
}
```

-- OBJECT IDENTITIES for MAU types

```
-- (see rpMauType and ifMauType of MAU-MIB for usage)
-- The following definitions has been moved from RFC 3636 and
-- no longer appear in its revision.
```

```
dot3MauType OBJECT IDENTIFIER ::= { mib-2 snmpDot3MauMgt(26) 4 }
```

```
dot3MauTypeAUI OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "no internal MAU, view from AUI"
    REFERENCE    "[IEEE802.3], Section 7"
    ::= { dot3MauType 1 }
```

```
dot3MauType10Base5 OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "thick coax MAU"
    REFERENCE    "[IEEE802.3], Section 7"
    ::= { dot3MauType 2 }
```

```
dot3MauTypeFoirl OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "FOIRL MAU"
    REFERENCE    "[IEEE802.3], Section 9.9"
    ::= { dot3MauType 3 }
```

```
dot3MauType10Base2 OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "thin coax MAU"
    REFERENCE    "[IEEE802.3], Section 10"
    ::= { dot3MauType 4 }
```

```
dot3MauType10BaseT OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "UTP MAU.
                  Note that it is strongly recommended that
                  agents return either dot3MauType10BaseTHD or
                  dot3MauType10BaseTFD if the duplex mode is
                  known. However, management applications should
                  be prepared to receive this MAU type value from
                  older agent implementations."
    REFERENCE    "[IEEE802.3], Section 14"
    ::= { dot3MauType 5 }
```

```
dot3MauType10BaseFP OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "passive fiber MAU"
    REFERENCE    "[IEEE802.3], Section 16"
    ::= { dot3MauType 6 }
```

```
dot3MauType10BaseFB OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "sync fiber MAU"
    REFERENCE       "[IEEE802.3], Section 17"
    ::= { dot3MauType 7 }

dot3MauType10BaseFL OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "async fiber MAU.
                    Note that it is strongly recommended that
                    agents return either dot3MauType10BaseFLHD or
                    dot3MauType10BaseFLFD if the duplex mode is
                    known. However, management applications should
                    be prepared to receive this MAU type value from
                    older agent implementations."
    REFERENCE       "[IEEE802.3], Section 18"
    ::= { dot3MauType 8 }

dot3MauType10Broad36 OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "broadband DTE MAU.
                    Note that 10BROAD36 MAUs can be attached to
                    interfaces but not to repeaters."
    REFERENCE       "[IEEE802.3], Section 11"
    ::= { dot3MauType 9 }

----- new since RFC 1515:
dot3MauType10BaseTHD OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "UTP MAU, half duplex mode"
    REFERENCE       "[IEEE802.3], Section 14"
    ::= { dot3MauType 10 }

dot3MauType10BaseTFD OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "UTP MAU, full duplex mode"
    REFERENCE       "[IEEE802.3], Section 14"
    ::= { dot3MauType 11 }

dot3MauType10BaseFLHD OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "async fiber MAU, half duplex mode"
    REFERENCE       "[IEEE802.3], Section 18"
    ::= { dot3MauType 12 }

dot3MauType10BaseFLFD OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "async fiber MAU, full duplex mode"
```



```
REFERENCE    "[IEEE802.3], Section 18"
::= { dot3MauType 13 }

dot3MauType100BaseT4 OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "4 pair category 3 UTP"
    REFERENCE    "[IEEE802.3], Section 23"
    ::= { dot3MauType 14 }

dot3MauType100BaseTXHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "2 pair category 5 UTP, half duplex mode"
    REFERENCE    "[IEEE802.3], Section 25"
    ::= { dot3MauType 15 }

dot3MauType100BaseTXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "2 pair category 5 UTP, full duplex mode"
    REFERENCE    "[IEEE802.3], Section 25"
    ::= { dot3MauType 16 }

dot3MauType100BaseFXHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "X fiber over PMT, half duplex mode"
    REFERENCE    "[IEEE802.3], Section 26"
    ::= { dot3MauType 17 }

dot3MauType100BaseFXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "X fiber over PMT, full duplex mode"
    REFERENCE    "[IEEE802.3], Section 26"
    ::= { dot3MauType 18 }

dot3MauType100BaseT2HD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "2 pair category 3 UTP, half duplex mode"
    REFERENCE    "[IEEE802.3], Section 32"
    ::= { dot3MauType 19 }

dot3MauType100BaseT2FD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "2 pair category 3 UTP, full duplex mode"
    REFERENCE    "[IEEE802.3], Section 32"
    ::= { dot3MauType 20 }

----- new since RFC 2239:
dot3MauType100BaseXHD OBJECT-IDENTITY
    STATUS      current
```

```
DESCRIPTION "PCS/PMA, unknown PMD, half duplex mode"
REFERENCE   "[IEEE802.3], Section 36"
::= { dot3MauType 21 }
```

```
dot3MauType1000BaseXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "PCS/PMA, unknown PMD, full duplex mode"
    REFERENCE   "[IEEE802.3], Section 36"
    ::= { dot3MauType 22 }
```

```
dot3MauType1000BaseLXHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Fiber over long-wavelength laser, half duplex
mode"
    REFERENCE   "[IEEE802.3], Section 38"
    ::= { dot3MauType 23 }
```

```
dot3MauType1000BaseLXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Fiber over long-wavelength laser, full duplex
mode"
    REFERENCE   "[IEEE802.3], Section 38"
    ::= { dot3MauType 24 }
```

```
dot3MauType1000BaseSXHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Fiber over short-wavelength laser, half
duplex mode"
    REFERENCE   "[IEEE802.3], Section 38"
    ::= { dot3MauType 25 }
```

```
dot3MauType1000BaseSXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Fiber over short-wavelength laser, full
duplex mode"
    REFERENCE   "[IEEE802.3], Section 38"
    ::= { dot3MauType 26 }
```

```
dot3MauType1000BaseCXHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Copper over 150-Ohm balanced cable, half
duplex mode"
    REFERENCE   "[IEEE802.3], Section 39"
    ::= { dot3MauType 27 }
```

```
dot3MauType1000BaseCXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Copper over 150-Ohm balanced cable, full
```

```
        duplex mode"
REFERENCE   "[IEEE802.3], Section 39"
 ::= { dot3MauType 28 }

dot3MauType1000BaseTHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Four-pair Category 5 UTP, half duplex mode"
    REFERENCE   "[IEEE802.3], Section 40"
    ::= { dot3MauType 29 }

dot3MauType1000BaseTFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "Four-pair Category 5 UTP, full duplex mode"
    REFERENCE   "[IEEE802.3], Section 40"
    ::= { dot3MauType 30 }

----- new since RFC 2668:
dot3MauType10GigBaseX OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "X PCS/PMA, unknown PMD."
    REFERENCE   "[IEEE802.3], Section 48"
    ::= { dot3MauType 31 }

dot3MauType10GigBaseLX4 OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "X fiber over WDM optics"
    REFERENCE   "[IEEE802.3], Section 53"
    ::= { dot3MauType 32 }

dot3MauType10GigBaseR OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "R PCS/PMA, unknown PMD."
    REFERENCE   "[IEEE802.3], Section 49"
    ::= { dot3MauType 33 }

dot3MauType10GigBaseER OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "R fiber over 1550 nm optics"
    REFERENCE   "[IEEE802.3], Section 52"
    ::= { dot3MauType 34 }

dot3MauType10GigBaseLR OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "R fiber over 1310 nm optics"
    REFERENCE   "[IEEE802.3], Section 52"
    ::= { dot3MauType 35 }

dot3MauType10GigBaseSR OBJECT-IDENTITY
```

```
STATUS      current
DESCRIPTION "R fiber over 850 nm optics"
REFERENCE   "[IEEE802.3], Section 52"
::= { dot3MauType 36 }

dot3MauType10GigBaseW OBJECT-IDENTITY
STATUS      current
DESCRIPTION "W PCS/PMA, unknown PMD."
REFERENCE   "[IEEE802.3], Section 49 and 50"
::= { dot3MauType 37 }

dot3MauType10GigBaseEW OBJECT-IDENTITY
STATUS      current
DESCRIPTION "W fiber over 1550 nm optics"
REFERENCE   "[IEEE802.3], Section 52"
::= { dot3MauType 38 }

dot3MauType10GigBaseLW OBJECT-IDENTITY
STATUS      current
DESCRIPTION "W fiber over 1310 nm optics"
REFERENCE   "[IEEE802.3], Section 52"
::= { dot3MauType 39 }

dot3MauType10GigBaseSW OBJECT-IDENTITY
STATUS      current
DESCRIPTION "W fiber over 850 nm optics"
REFERENCE   "[IEEE802.3], Section 52"
::= { dot3MauType 40 }

----- new since RFC 3636:
dot3MauType10GigBaseCX4 OBJECT-IDENTITY
STATUS      current
DESCRIPTION "X copper over 8 pair 100-Ohm balanced cable"
REFERENCE   "[IEEE802.3], Section 54"
::= { dot3MauType 41 }

dot3MauType2BaseTL OBJECT-IDENTITY
STATUS      current
DESCRIPTION "Voice grade UTP copper, up to 2700m, optional PAF"
REFERENCE   "[IEEE802.3], Sections 61 and 63"
::= { dot3MauType 42 }

dot3MauType10PasSTS OBJECT-IDENTITY
STATUS      current
DESCRIPTION "Voice grade UTP copper, up to 750m, optional PAF"
REFERENCE   "[IEEE802.3], Sections 61 and 62"
::= { dot3MauType 43 }
```

```
dot3MauType100BaseBX10D OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber OLT, long wavelength, 10km"
    REFERENCE       "[IEEE802.3], Section 58"
    ::= { dot3MauType 44 }
```

```
dot3MauType100BaseBX10U OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber ONU, long wavelength, 10km"
    REFERENCE       "[IEEE802.3], Section 58"
    ::= { dot3MauType 45 }
```

```
dot3MauType100BaseLX10 OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "Two single-mode fibers, long wavelength, 10km"
    REFERENCE       "[IEEE802.3], Section 58"
    ::= { dot3MauType 46 }
```

```
dot3MauType1000BaseBX10D OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber OLT, long wavelength, 10km"
    REFERENCE       "[IEEE802.3], Section 59"
    ::= { dot3MauType 47 }
```

```
dot3MauType1000BaseBX10U OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber ONU, long wavelength, 10km"
    REFERENCE       "[IEEE802.3], Section 59"
    ::= { dot3MauType 48 }
```

```
dot3MauType1000BaseLX10 OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "Two single-mode fiber, long wavelength, 10km"
    REFERENCE       "[IEEE802.3], Section 59"
    ::= { dot3MauType 49 }
```

```
dot3MauType1000BasePX10D OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber EPON OLT, 10km"
    REFERENCE       "[IEEE802.3], Section 60"
    ::= { dot3MauType 50 }
```

```
dot3MauType1000BasePX10U OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber EPON ONU, 10km"
    REFERENCE       "[IEEE802.3], Section 60"
    ::= { dot3MauType 51 }
```

```
dot3MauType1000BasePX20D OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber EPON OLT, 20km"
    REFERENCE       "[IEEE802.3], Section 60"
    ::= { dot3MauType 52 }
```

```
dot3MauType1000BasePX20U OBJECT-IDENTITY
    STATUS          current
    DESCRIPTION     "One single-mode fiber EPON ONU, 20km"
    REFERENCE       "[IEEE802.3], Section 60"
    ::= { dot3MauType 53 }
```

END

6. Security Considerations

The IANA-MAU-MIB does not define any management objects. Instead, it defines a set of textual conventions which are used by the MAU-MIB and may be used by other MIB modules to define management objects. Meaningful security considerations can only be written for MIB modules that define management objects.

There are a number of management objects defined in the MAU-MIB that have a MAX-ACCESS clause of read-write. Setting these objects can have a serious effect on the operation of the network, including:

- o enabling or disabling a MAU
- o changing a MAU's default type
- o enabling, disabling, or restarting autonegotiation
- o modifying the capabilities that a MAU advertizes during autonegotiation.

Such objects may be considered sensitive or vulnerable in some network environments. The support for SET operations in a non-secure environment without proper protection can have a negative effect on network operations.

Some of the readable objects in the MAU-MIB module (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. In some environments, it may be undesirable to allow unauthorized parties to access statistics or status information about individual links in a network. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP.

SNMP versions prior to SNMPv3 did not include adequate security. Even if the network itself is secure (for example by using IPsec), even then, there is no control as to who on the secure network is allowed to access and GET/SET (read/change/create/delete) the objects in the MAU-MIB module.

It is RECOMMENDED that the implementors consider the security features as provided by the SNMPv3 framework (see [RFC3410], section 8), including full support for the SNMPv3 cryptographic mechanisms (for authentication and privacy).

Furthermore, deployment of SNMP versions prior to SNMPv3 is NOT RECOMMENDED. Instead, it is RECOMMENDED to deploy SNMPv3 and to enable cryptographic security. It is then a customer/operator responsibility to ensure that the SNMP entity giving access to an instance of the MAU-MIB module is properly configured to give access to the objects only to those principals (users) that have legitimate rights to indeed GET or SET (change/create/delete) them.

7. IANA Considerations

This document defines first version of the IANA-maintained IANA-MAU-MIB module. It is intended that each new MAU type, Media Available state, Auto Negotiation capability, and/or Jack type defined by the IEEE 802.3 working group and approved for publication in a revision of IEEE Std 802.3 will be added to the IANA-maintained MIB module, provided that it is suitable for being managed by the base objects in the MAU-MIB module.

For each new MAU type added, a short description of the MAU technology and, wherever possible, a reference to a publicly available specification SHOULD be specified. An Expert Review, as defined in RFC 2434 [RFC2434], is REQUIRED, for each modification.

8. Acknowledgments

This document was produced by the IETF Ethernet Interfaces and Hub MIB Working Group, whose efforts were greatly advanced by the contributions of the following people:

Mike Heard

John Flick

Dan Romascanu

This document is based on the Proposed Standard MAU MIB, RFC 3636 [RFC3636], edited by John Flick of Hewlett-Packard, and produced by

the Ethernet Interfaces and Hub MIB Working Group. It extends that document by moving the object identities and textual conventions for MAU types into a IANA-maintained MIB module. In addition, support is provided for the EFM and 10GBASE-CX4 MAUs as defined in [IEEE802.3ah] and [IEEE802.3ak] respectively.

RFC 3636, in turn, was based on the Proposed Standard MAU MIB, RFC 2668 [RFC2668], edited by John Flick of Hewlett-Packard and Andrew Smith, then of Extreme Networks, and produced by the Ethernet Interfaces and Hub MIB Working Group. It extends that document by providing support for 10 Gb/s MAUs as defined in [IEEE802.3ae].

RFC 2668, in turn, was based on the Proposed Standard MAU MIB, RFC 2239 [RFC2239], edited by Kathryn de Graaf, then of 3Com, and Dan Romascanu, then of Madge Networks, and produced by the Ethernet Interfaces and Hub MIB Working Group. It extended that document by providing support for 1000 Mb/sec MAUs, PAUSE negotiation and remote fault status as defined in [IEEE802.3].

RFC 2239, in turn, was based on the Proposed Standard MAU MIB, RFC 1515 [RFC1515], edited by Donna McMaster, then of SynOptics Communications, Keith McCloghrie, then of Hughes LAN Systems, and Sam Roberts, then of Farallon Computing, and produced by the Hub MIB Working Group. It extends that document by providing support for 100 Mb/sec MAUs, full duplex MAUs, auto-negotiation, and jack management as defined in [IEEE802.3].

9. References

9.1. Normative References

- [IEEE802.3] IEEE, "IEEE Standard for Information technology - Telecommunications and information exchange between systems - Local and metropolitan area networks - Specific requirements - Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications", IEEE Std 802.3-2005, December 2005.
- [IEEE802.3ae] IEEE, "IEEE Standard for Information technology - Telecommunications and information exchange between systems - Local and metropolitan area networks - Specific requirements - Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications - Media Access Control (MAC) Parameters, Physical Layer and Management Parameters for 10 Gb/s Operation", IEEE Std 802.3ae-2002, August 2002.

- [IEEE802.3ah] IEEE, "Information technology - Telecommunications and information exchange between systems - Local and metropolitan area networks - Specific requirements - Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications - Media Access Control Parameters, Physical Layers and Management Parameters for Subscriber Access Networks", IEEE Std 802.3ah-2004, September 2004.
- [IEEE802.3ak] IEEE, "IEEE Standard for Information technology - Telecommunications and information exchange between systems - Local and metropolitan area networks - Specific requirements - Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications - Physical Layer and Management Parameters for 10Gb/s Operation, Type 10GBASE-CX4", IEEE Std 802.3ak-2004, March 2004.
- [RFC2108] de Graaf, K., Romascanu, D., McMaster, D., and K. McCloghrie, "Definitions of Managed Objects for IEEE 802.3 Repeater Devices using SMIV2", RFC 2108, February 1997.
- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", BCP 14, RFC 2119, March 1997.
- [RFC2434] Narten, T. and H. Alvestrand, "Guidelines for Writing an IANA Considerations Section in RFCs", BCP 26, RFC 2434, October 1998.
- [RFC2578] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Structure of Management Information Version 2 (SMIV2)", STD 58, RFC 2578, April 1999.
- [RFC2579] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Textual Conventions for SMIV2", STD 58, RFC 2579, April 1999.
- [RFC2580] McCloghrie, K., Perkins, D., and J. Schoenwaelder, "Conformance Statements for SMIV2", STD 58, RFC 2580, April 1999.
- [RFC2863] McCloghrie, K. and F. Kastenholz, "The Interfaces Group MIB", RFC 2863, June 2000.

- [RFC3635] Flick, J., "Definitions of Managed Objects for the Ethernet-like Interface Types", RFC 3635, September 2003.

9.2. Informative References

- [RFC1515] McMaster, D., McCloghrie, K., and S. Roberts, "Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs)", RFC 1515, September 1993.
- [RFC2239] de Graaf, K., Romascanu, D., McMaster, D., McCloghrie, K., and S. Roberts, "Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs) using SMIV2", RFC 2239, November 1997.
- [RFC2668] Smith, A., Flick, J., de Graaf, K., Romascanu, D., McMaster, D., McCloghrie, K., and S. Roberts, "Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs)", RFC 2668, August 1999.
- [RFC3410] Case, J., Mundy, R., Partain, D., and B. Stewart, "Introduction and Applicability Statements for Internet-Standard Management Framework", RFC 3410, December 2002.
- [RFC3418] Presuhn, R., "Management Information Base (MIB) for the Simple Network Management Protocol (SNMP)", STD 62, RFC 3418, December 2002.
- [RFC3636] Flick, J., "Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs)", RFC 3636, September 2003.
- [RFC3637] Heard, C., "Definitions of Managed Objects for the Ethernet WAN Interface Sublayer", RFC 3637, September 2003.

Author's Address

Edward Beili
Actelis Networks
Bazel 25
Petach-Tikva
Israel

Phone: +972-3-924-3491
EMail: edward.beili@actelis.com

Full Copyright Statement

Copyright (C) The IETF Trust (2007).

This document is subject to the rights, licenses and restrictions contained in BCP 78, and except as set forth therein, the authors retain all their rights.

This document and the information contained herein are provided on an "AS IS" basis and THE CONTRIBUTOR, THE ORGANIZATION HE/SHE REPRESENTS OR IS SPONSORED BY (IF ANY), THE INTERNET SOCIETY, THE IETF TRUST AND THE INTERNET ENGINEERING TASK FORCE DISCLAIM ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OR ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

Intellectual Property

The IETF takes no position regarding the validity or scope of any Intellectual Property Rights or other rights that might be claimed to pertain to the implementation or use of the technology described in this document or the extent to which any license under such rights might or might not be available; nor does it represent that it has made any independent effort to identify any such rights. Information on the procedures with respect to rights in RFC documents can be found in BCP 78 and BCP 79.

Copies of IPR disclosures made to the IETF Secretariat and any assurances of licenses to be made available, or the result of an attempt made to obtain a general license or permission for the use of such proprietary rights by implementers or users of this specification can be obtained from the IETF on-line IPR repository at <http://www.ietf.org/ipr>.

The IETF invites any interested party to bring to its attention any copyrights, patents or patent applications, or other proprietary rights that may cover technology that may be required to implement this standard. Please address the information to the IETF at ietf-ipr@ietf.org.

Acknowledgement

Funding for the RFC Editor function is currently provided by the Internet Society.

